
aiwa

aiwa SERVICE

NSX-V50
NSX-V52
NSX-V54
NSX-V51G

SERVICE MANUAL



COMPACT DISC STEREO
CASSETTE SYSTEM

- BASIC TAPE MECHANISM: 2ZM-3 PR6N
- BASIC CD MECHANISM: 4ZG-1TGFR
- TYPE. (50):HE.HR.HK.LH.U.C.G (52):U (54):U (51G):HD,HE.HR,HK.U

SYSTEM	CENTER UNIT	SPEAKER
NSX-V50 (HE,HR,HK,LH,U,C,G)	CX-NV50	SX-FNV50L (HE,HR,HK,LH) SX-FNV50 (U,C,G)
NSX-V52 (U)	CX-NV52	SX-FNV50 (U)
NSX-V54 (U)	CX-NV54	SX-FNV50 (U)
NSX-V51G (HD,HE,HR,HK,U)	CX-NV51G	SX-FNV50L (HD,HE,HR,HK) SX-FNV50 (U)

● If requiring information about the CD mechanism, see Service Manual of 4ZG-1T. (S/M Code No. 09-94C-086-20T).

S/M Code No. 09-957-108-20T

TABLE OF CONTENTS

SPECIFICATIONS 3
PROTECTION OF EYES FROM LASER BEAM DURING SERVICING 4
PRECAUTION TO REPLACE OPTICAL BLOCK 4
ELECTRICAL MAIN PARTS LIST ..... 5~9
TRANSISTOR ILLUSTRATION 10
BLOCK DIAGRAM-1 (MAIN / FRONT) 11, 12
BLOCK DIAGRAM-2 (TUNER: HE, HR, HK) 13
IC BLOCK DIAGRAM-1 14
WIRING-1 (MAIN: HE, HR, HK) 15, 16
SCHEMATIC DIAGRAM-1 (MAIN: HE, HR, HK) ..... 17~19
BLOCK DIAGRAM-3 (TUNER: LH, U, C, G) 20
WIRING-2 (MAIN: LH, U, C, G) 21, 22
SCHEMATIC DIAGRAM-2 (MAIN: LH, U, C, G) ..... 23~25
SCHEMATIC DIAGRAM-3 (MAIN: HD) ..... 26~28
WIRING-3 (MAIN: HD) 29, 30
BLOCK DIAGRAM-4 (TUNER: HD) 31
SCHEMATIC DIAGRAM-4 (FRONT) ..... 32~34
WIRING-4 (FRONT) 35, 36
WIRING-5 (DECK / S·WAVE) 37, 38
WIRING-6 (PT) 39
FL (BJ362GK) GRID ASSIGNMENT / ANODE CONNECTION 40
IC DESCRIPTION ..... 41~45
ELECTRICAL ADJUSTMENT / PRACTICAL SERVICE FIGURE ..... 46~51
IC BLOCK DIAGRAM-2 ..... 52~54
MECHANICAL EXPLODED VIEW 1 / 1 ..... 55, 56
MECHANICAL PARTS LIST 1 / 1 57
TAPE MECHANISM EXPLODED VIEW 1 / 1 ..... 58, 59
TAPE MECHANISM PARTS LIST 1 / 1 60
SPRING APPLICATION POSITION 61
SPEAKER EXPLODED VIEW 1 / 1 62
SPEAKER PARTS LIST 1 / 1 62
■ ACCESSORIES / PACKAGE LIST 63
REFERENCE NAME LIST 64

SPECIFICATIONS

Main unit CX-NV50/NV51G/NV52/NV54

FM Tuner section

Tuning range	HD: 76 MHz to 108 MHz EXCEPT HD: 87.5MHz to 108 MHz
Usable sensitivity (IHF)	13.2 dBf
Antenna terminals	75 ohms (unbalanced)

AM (MW) Tuner section

Tuning range	531 kHz to 1602 kHz (9 kHz step) 530 kHz to 1710 kHz (10 kHz step)
Usable sensitivity	350 µV/m
Antenna	Loop antenna

SW Tuner section (HE, HR, HK only)

Tuning range	SW1: 3.20 MHz to 7.30 MHz SW2: 9.50 MHz to 21.85 MHz
Antenna	Wire antenna

<Amplifier section>

Power output	HD, HE, HK, LH, G: 50 W+50 W (6 ohms, T.H.D. 10%, 1 kHz) HR: Rated 38 W+38 W (6 ohms, T.H.D. 1%, 1 kHz) Reference: 50 W+50 W (6 ohms, T.H.D. 10%, 1 kHz) C: 40 W+40 W (6 ohms, T.H.D. 1%, 1 kHz) U: FTC RULE 40 watts per channel, Min. RMS at 6 ohms, from 65 Hz to 12 kHz, with no more than 1% Total Harmonic Distortion
Total Harmonic distortion	HD, HE, HR, HK: 0.1% (50 W, 1 kHz, 6 ohms) LH, U, C, G: 0.1% (50 W, 1 kHz, 6 ohms. DIN-AUDIO)
Inputs	VIDEO/AUX: 150 mV adjustable MIC 1, MIC 2: 1 mV (10 kohms)
Outputs	1.0 Vp-p (75 ohms) SUPER WOOFER: 2.45 V SPEAKERS: accepts speakers of 6 ohms or more SURROUND SPEAKERS: accepts speakers of 16 ohms or more PHONES (stereo jack): accepts headphones of 32 ohms or more

Cassette deck section

Track format	4 tracks, 2 channels stereo
Frequency response	CrO_2 tape: 50 Hz-16000 Hz Normal tape: 50 Hz-15000 Hz
Signal-to-noise-ratio	60 dB (Dolby B NR ON, CrO_2 tape peak level above 5 kHz)
Recording system	AC bias
Heads	Deck 1: Playback head × 1 Deck 2: Recording/playback/erase head × 1

Compact disc player section

Laser	Semiconductor laser (λ=780 nm)
D-A converter	1 bit dual
Signal-to-noise ratio	85 dB (1 kHz, 0 dB)
Harmonic distortion	0.03% (1 kHz, 0 dB)
Wow and flutter	Unmeasurable
Video signal (CX-NV51G only)	NTSC/PAL color format

SPEAKER SYSTEM SX-FNV50/SX-FNV54/SX-FNV50L

Cabinet type	3 way, bass reflex with surround speaker (Magnetism sealed type)
Speaker	Woofer: 140 mm (5 5/8 in.) cone type Tweeter: 80 mm (3 1/4 in.) cone type Super tweeter: 50 mm (2 in.) ceramic type Surround speaker: 80 mm (3 1/4 in.) cone type
Impedance	Front speaker: 6 ohms Surround speaker: 16 ohms
Output sound pressure level	87 dB/W/m
Dimensions (W × H × D)	206 × 302 × 260 mm (8 1/8 × 12 × 10 1/4 in.)
Weight	3.6 kg (7 lbs. 15 oz.)

General


Power requirements	HD: 100-120 V/200-240 V AC, switchable 50/60 Hz HE, HR, HK, LH: 120 V/220-230 V/240 V AC, switchable 50/60 Hz U, C: 120 V AC fixed 60 Hz G: 230-240 V AC, fixed 50 Hz
Power consumption	HE, HK: 85 W LH, HD, HR: 100 W U, C: 110 W G: 120 W
Dimensions of main unit (W × H × D)	260 × 306.8 × 339.5 mm (10 1/4 × 12 1/8 × 13 3/8 in.)
Weight of main unit	HD, HE, U, C: 7.3 kg (16 lbs. 2 oz.) HR, HK, LH, G: 7.5 kg (16 lbs. 9 oz.)

- Design and specifications are subject to change without notice.
- Dolby noise reduction manufactured under license from Dolby Laboratories Licensing Corporation.
  "DOLBY" and the double-D symbol ⧈ are trademarks of Dolby Laboratories Licensing Corporation.

PROTECTION OF EYES FROM LASER BEAM DURING SERVICING

This set employs laser. Therefore, be sure to follow carefully the instructions below when servicing.

WARNING!
WHEN SERVICING, DO NOT APPROACH THE LASER EXIT WITH THE EYE TOO CLOSELY. IN CASE IT IS NECESSARY TO CONFIRM LASER BEAM EMISSION. BE SURE TO OBSERVE FROM A DISTANCE OF MORE THAN 30cm FROM THE SURFACE OF THE OBJECTIVE LENS ON THE OPTICAL PICK-UP BLOCK.



- Caution: Invisible laser radiation when open and interlocks defeated avoid exposure to beam.
- Advarsel: Usynlig laserståling ved åbning, når sikkerhedsafbrydere er ude af funktion. Undgå udsættelse for stråling.

VAROITUS!
Laiteen Käyttäminen muulla kuin tässä käyttöohjeessa mainitulla tavalla saattaa altistaa käyt-täjän turvallisuusluokan 1 ylittävälle näkymättömälle lasersäteilylle.

VARNING!
Om apparaten används på annat sätt än vad som specificeras i denna bruksanvising, kan användaren utsättas för osynling laserstrålning, som överskrider gränsen för laserklass 1.

CAUTION
Use of controls or adjustments or performance of procedures other than those specified herein may result in hazardous radiation exposure.

ATTENTION
L'utilisation de commandes, réglages ou procédures autres que ceux spécifiés peut entraîner une dangereuse exposition aux radiations.

ADVARSEL!
Usynlig laserståling ved åbning, når sikkerhedsafbrydereer ude af funktion. Undgå udsættelse for stråling.


This Compact Disc player is classified as a CLASS 1 LASER product.
The CLASS 1 LASER PRODUCT label is located on the rear exterior.

CLASS 1	LASER PRODUCT
KLASSE 1	LASER PRODUKT
LUOKAN 1	LASER LAITE
KLASS 1	LASER APPARAT

Precaution to replace Optical block (KSS-210A)

Body or clothes electrostatic potential could ruin laser diode in the optical block. Be sure to ground body and workbench, and use care the clothes do not touch the diode.

1) After the connection, remove solder shown in the right figure.



ELECTRICAL MAIN PARTS LIST

※ 1G=NV51G

DESCRIPTIONで判断できない物は "REFERENCE NAME LIST" を参照してください。
If can't understand for Description please kindly refer to "REFERENCE NAME LIST".

REF. NO	PART NO.	カンリ NO.	DESCRIPTION
IC			
	87-020-454-010		IC,DN6851
	85-NF6-602-010		IC,LC866432V-5752
	87-070-083-010		IC,GP1U281X
	87-001-582-010		IC,STK41522
	87-070-121-010		IC,HA12185NT
	87-070-232-010		IC,BA3834S
	87-017-375-080		IC,TC4094BF
	87-001-874-010		IC,HA12134A
	87-017-673-010		IC,BA3837
	87-017-022-080		IC,NJM2068M-D(T1)
	87-017-374-010		IC,TC4094BP
	87-017-804-010		IC,BU4052BCP
	87-070-184-040		IC,M65846FP-600D
	87-017-787-010		IC,M62412P
	87-070-127-010		IC,LC72131
	87-002-642-080		IC,TA8124F<HD>
	87-001-607-080		IC,NJM4558M
	87-017-714-010		IC,LA1836
	87-017-675-080		IC,M65840FP
			<1GHE,1GHR,1GHK,1GU,HD>
	87-001-486-080		IC,ICP-N15T104<1GU,U,C>
TRANSISTOR			
	87-026-463-080		TR,2SA933S(RS)
	89-213-702-010		TR,2SB1370E
	87-026-609-080		TR,KTA1266GR
	87-026-610-080		TR,KTC3198GR
	89-327-125-080		C-TR,2SC2712GR
	89-332-665-080		TR,2SC3266GR
	89-420-053-080		TR,2SD2005R<1GU,U,C>
	89-111-625-080		C-TR,2SA1162GR
	89-113-137-880		TR,2SA1318TU
	87-026-235-080		C-TR,DTC114EK
	89-333-266-080		C-TR,2SC3326B
	87-026-211-080		C-TR,DTA144EK
	87-026-232-080		C-TR,DTA144WK
	87-026-226-080		C-TR,DTA143EK
	89-503-655-680		FET,2SK365GR/BL
	89-333-317-080		TR,2SC3331T
	89-109-521-080		TR,2SA952K
	89-112-965-080		TR,2SA1296GR
	89-406-555-080		TR,2SD655E
	87-026-214-080		TR,DTA114YS
	87-026-219-080		TR,DTA144ES<HD>
	87-026-213-080		C-TR,DTC114YK<HD>
	89-327-143-080		TR,2SC2714(O)
	89-318-154-080		TR,2SC1815Y
			<EXCEPT 1GU,HD,LH,U,C,G>
	87-026-462-080		TR,2SC1740S(RS)
			<EXCEPT 1GU,HD,LH,U,C,G>
	89-320-011-080		TR,2SC2001K
			<EXCEPT 1GU,HD,LH,U,C,G>
	89-505-434-580		C-FET,2SK543(4/5)
	89-318-155-080		TR,2SC1815GR
			<EXCEPT 1GU,HD,LH,U,C,G>
DIODE			
	87-017-978-080		DIODE,1N4003
	87-020-027-080		C-DIODE,1SS184
	87-020-125-080		C-DIODE,1SS181
	87-020-465-080		DIODE,ISS133
	87-017-174-080		ZENER,HZS11A3L
	87-070-150-080		ZENER,MTZJ33D
	87-002-225-010		DIODE,DBF 40C-K10
			<1GHR,1GU,HD,50HR,LH,U,C,G>
	87-020-691-080		DIODE,1SS132 T-72
	87-002-608-080		DIODE,DSF10TC
	87-001-914-080		ZENER,UTZJ6.2B
	87-070-136-080		ZENER,MTZJ5.1B
	87-020-331-080		C-DIODE,DAN202K
	87-001-290-080		ZENER,HZS6B1L
	87-020-330-080		C-DIODE,DAP202K
	87-001-559-080		DIODE,1SS131
	87-017-148-080		ZENER,HZS6A1L
	87-020-125-009		C-DIODE,1SS181
			<EXCEPT 1GU,HD,LH,U,C,G>
MAIN C.B			
C102	87-010-390-090		CAP,ELECT 25-3300SME<EXCEPT HD>
C102	87-010-399-090		CAP,ELECT 35-3300SME<HD>
C104	87-010-235-080		CAP,E 470-16 SME
C105	87-010-381-080		CAP,E 330-16 SME
C106	87-010-764-080		CAP,E 47-63
C107	87-010-406-080		CAP,E 22-50 SME
C108	87-010-406-080		CAP,E 22-50 SME
C109	87-010-263-080		CAP,E 100-10
C112	87-010-382-080		CAP,E 22-25 SME
			<1GHE,1GHR,1GHK,1GU,HD>
C112	87-010-406-080		CAP,E 22-50 SME
			<50HE,50HR,50HK,LH,U,C,G>
C113	87-010-403-080		CAP,E 3.3-50 SME
C115	87-016-247-080		C-CAP,0.1-50F
C116	87-010-179-080		C-CAP,S 1200P-50 B
			<50HE,50HR,50HK,LH,U,C,G>
C116	87-012-140-080		C-CAP,S 470P-50 CH
			<1GHE,1GHR,1GHK,1GU,HD>
C117	87-010-196-080		C-CAP,S 0.1-25 F
C118	87-010-196-080		C-CAP,S 0.1-25 F
C119	87-010-196-080		C-CAP,S 0.1-25 F
C126	87-016-055-090		CAP,E 3300-42 HI-R
C127	87-016-055-090		CAP,E 3300-42 HI-R
C128	87-012-368-080		C-CAP,S 0.1-50 F
C131	87-012-368-080		C-CAP,S 0.1-50 F
C135	87-012-368-080		C-CAP,S 0.1-50 F<1GU,U,C>
C152	87-010-260-080		CAP,E 47-25 SME
C213	87-010-401-080		CAP,E 1-50 SME
C214	87-010-401-080		CAP,E 1-50 SME
C215	87-010-182-080		C-CAP,S 2200P-50 B
C216	87-010-182-080		C-CAP,S 2200P-50 B
C217	87-010-404-080		CAP,E 4.7-50 SME
C218	87-010-404-080		CAP,E 4.7-50 SME
C221	87-010-400-080		CAP,E 0.47-50 SME<1GU,U,C>
C221	87-010-401-080		CAP,E 1-50 SME<EXCEPT 1GU,U,C>
C222	87-010-400-080		CAP,E 0.47-50 SME<1GU,U,C>
C222	87-010-401-080		CAP,E 1-50 SME<EXCEPT 1GU,U,C>
C223	87-010-260-080		CAP,E 47-25 SME
C224	87-010-260-080		CAP,E 47-25 SME
C225	87-010-260-080		CAP,E 47-25 SME
C226	87-010-260-080		CAP,E 47-25 SME
C227	87-018-209-080		CAP,TC-U 0.1-50 F
C228	87-018-209-080		CAP,TC-U 0.1-50 F
C231	87-010-196-080		C-CAP,S 0.1-25 F
C243	87-010-154-080		C-CAP,S 10P-50 CH
C244	87-015-879-080		C-CAP,10P CH
C245	87-018-208-080		CAP,TC-U 0.047-50 F
C250	87-010-197-080		C-CAP,S 0.01-25 B
C297	87-010-260-080		CAP,E 47-25 SME<EXCEPT 1GU,U,C>
C298	87-010-260-080		CAP,E 47-25 SME<EXCEPT 1GU,U,C>
C303	87-012-157-080		C-CAP,S 330P-50 CH
C304	87-012-157-080		C-CAP,S 330P-50 CH
C305	87-012-155-080		C-CAP,S 180P-50 CH
C306	87-012-155-080		C-CAP,S 180P-50 CH
C307	87-010-197-080		C-CAP,S 0.01-25 B
C308	87-010-197-080		C-CAP,S 0.01-25 B

REF. NO	PART NO.	カンリ NO.	DESCRIPTION
C313	87-010-181-080		C-CAP,S 1800P-50 B
C314	87-010-181-080		C-CAP,S 1800P-50 B
C315	87-010-179-080		C-CAP,S 1200P-50 B
C316	87-010-179-080		C-CAP,S 1200P-50 B
C317	87-012-142-080		C-CAP,S 0.33-16 F
C318	87-010-955-080		C-CAP,0.33-16 R
C319	87-012-141-080		C-CAP,S 0.22-16 F
C320	87-012-141-080		C-CAP,S 0.22-16 F
C321	87-010-196-080		C-CAP,S 0.1-25 F
C322	87-010-196-080		C-CAP,S 0.1-25 F
C324	87-010-260-080		CAP,E 47-25 SME
C325	87-010-370-080		CAP,E 330-6.3 SME
C326	87-010-196-080		C-CAP,S 0.1-25 F
C332	87-010-196-080		C-CAP,S 0.1-25 F
C334	87-010-406-080		CAP,E 22-50 SME
			<50HE,50HR,50HK,LH,U,C,G>
C335	87-010-805-080		C-CAP,S 1-16F
C336	87-010-805-080		C-CAP,S 1-16F
C351	87-012-154-080		C-CAP,S 150P-50 CH
C352	87-012-154-080		C-CAP,S 150P-50 CH
C451	87-012-140-080		C-CAP,S 470P-50 CH
C452	87-012-140-080		C-CAP,S 470P-50 CH
C453	87-010-178-080		C-CAP,S 1000P-50 B
C454	87-010-175-080		C-CAP,S 560P-50 SL
C455	87-010-175-080		C-CAP,S 560P-50 SL
C456	87-010-260-080		CAP,E 47-25 SME
C457	87-010-197-080		C-CAP,S 0.01-25 B
C458	87-010-183-080		C-CAP,S 2700P-50 B
C459	87-010-183-080		C-CAP,S 2700P-50 B
C460	87-010-183-080		C-CAP,S 2700P-50 B
C470	87-010-196-080		C-CAP,S 0.1-25 F
C501	87-010-177-080		C-CAP,S 820P-50 SL
C502	87-010-177-080		C-CAP,S 820P-50 SL
C503	87-012-155-080		C-CAP,S 180P-50 CH
C504	87-012-155-080		C-CAP,S 180P-50 CH
C515	87-010-545-080		CAP,E 0.22-50 SME
C516	87-010-545-080		CAP,E 0.22-50 SME
C519	87-010-196-080		C-CAP,S 0.1-25 F
C521	87-010-197-080		C-CAP,S 0.01-25 B
C522	87-010-318-080		C-CAP,S 47P-50 CH
C523	87-010-197-080		C-CAP,S 0.01-25 B
C524	87-010-402-080		CAP,E 2.2-50 SME
C530	87-010-194-080		C-CAP,S 0.047-25 F
C531	87-010-545-080		CAP,E 0.22-50 SME
C532	87-010-382-080		CAP,E 22-25 SME
C533	87-010-404-080		CAP,E 4.7-50 SME
C534	87-010-404-080		CAP,E 4.7-50 SME
C535	87-010-404-080		CAP,E 4.7-50 SME
C536	87-010-404-080		CAP,E 4.7-50 SME
C537	87-018-209-080		CAP,TC-U 0.1-50 F
C538	87-010-384-080		CAP,E 100-25 SME
C539	87-010-196-080		C-CAP,S 0.1-25 F
			<1GHE,1GHR,1GHK,1GU,HD>
C540	87-010-196-080		C-CAP,S 0.1-25 F
C541	87-010-196-080		C-CAP,S 0.1-25 F
C543	87-010-546-080		CAP,E 0.33-50 SME
C544	87-010-546-080		CAP,E 0.33-50 SME
C545	87-010-400-080		CAP,E 0.47-50 SME
C546	87-010-400-080		CAP,E 0.47-50 SME
C547	87-010-426-080		C-CAP,S 0.012-25 B
			<EXCEPT 1GU,HD,LH,U,C,G>
C547	87-010-428-080		C-CAP,S 0.015-25 B<HD,G>
C547	87-010-198-080		C-CAP,S 0.022-25 B<1GU,LH,U,C>
C548	87-010-426-080		C-CAP,S 0.012-25 B
			<EXCEPT 1GU,HD,LH,U,G>
C548	87-010-428-080		C-CAP,S 0.015-25 B<HD,G>
C548	87-010-198-080		C-CAP,S 0.022-25 B<1GU,LH,U>
C549	87-018-209-080		CAP,TC-U 0.1-50 F
C550	87-010-183-080		C-CAP,S 2700P-50 B
C553	87-010-178-080		C-CAP,S 1000P-50 B
			<1GU,LH,U,C,G>
C553	87-010-183-080		C-CAP,S 2700P-50 B
			<EXCEPT 1GU,HD,LH,U,C,G>
C554	87-010-178-080		C-CAP,S 1000P-50 B
			<1GU,LH,U,C,G>
C554	87-010-183-080		C-CAP,S 2700P-50 B
			<EXCEPT 1GU,HD,LH,U,C,G>
C557	87-010-178-080		C-CAP,S 1000P-50 B<EXCEPT HD>
C558	87-010-178-080		C-CAP,S 1000P-50 B
C641	87-010-196-080		C-CAP,S 0.1-25 F
C642	87-010-196-080		C-CAP,S 0.1-25 F
			<EXCEPT LH,U,C,G>
C701	87-010-381-080		CAP,E 330-16 SME
C702	87-010-404-080		CAP,E 4.7-50 SME
C703	87-010-197-080		C-CAP,S 0.01-25 B
C704	87-010-197-080		C-CAP,S 0.01-25 B
C711	87-010-263-080		CAP,E 100-10 SME 5X11
C712	87-010-196-080		C-CAP,S 0.1-25 F
C721	87-010-313-080		C-CAP,S 18P-50 CH<HD>
C722	87-010-311-080		C-CAP,S 12P-50 CH
C723	87-010-178-080		C-CAP,S 1000P-50 B
C725	87-010-178-080		C-CAP,S 1000P-50 B
C727	87-010-196-080		C-CAP,S 0.1-25 F
C728	87-010-248-080		CAP,E 220-10 SME
C739	87-010-313-080		C-CAP,S 18P-50 CH<HD>
C741	87-010-545-080		CAP,E 0.22-50 SME<HD>
C742	87-010-154-080		C-CAP,S 10P-50 CH<HD>
C743	87-010-404-080		CAP,E 4.7-50 SME<HD>
C744	87-010-260-080		CAP,E 47-25 SME<HD>
C745	87-010-545-080		CAP,E 0.22-50 SME<HD>
C746	87-010-545-080		CAP,E 0.22-50 SME<HD>
C747	87-010-197-080		C-CAP,S 0.01-25 B<HD>
C748	87-010-198-080		C-CAP,S 0.022-25 B<HD>
C749	87-010-248-080		CAP,E 220-10 SME<HD>
C753	87-010-404-080		CAP,E 4.7-50 SME<HD>
C770	87-010-405-080		CAP,E 10-50 SME
C771	87-010-405-080		CAP,E 10-50 SME
C772	87-010-194-080		C-CAP,S 0.047-25 F
C773	87-010-196-080		C-CAP,S 0.1-25 F
C774	87-010-263-080		CAP,E 100-10 SME 5X11
C775	87-010-405-080		CAP,E 10-50 SME
C776	87-010-197-080		C-CAP,S 0.01-25 B
			<1GU,HD,LH,U,C,G>
C777	87-010-400-080		CAP,E 0.47-50 SME
C778	87-010-401-080		CAP,E 1-50 SME
C779	87-010-401-080		CAP,E 1-50 SME
C780	87-010-197-080		C-CAP,S 0.01-25 B
C781	87-010-401-080		CAP,E 1-50 SME<HD>
C781	87-010-405-080		CAP,E 10-50 SME<EXCEPT HD>
C782	87-010-401-080		CAP,E 1-50 SME<HD>
C782	87-010-405-080		CAP,E 10-50 SME<EXCEPT HD>
C783	87-010-182-080		C-CAP,S 2200P-50 B<HD>
C784	87-010-182-080		C-CAP,S 2200P-50 B<HD>
C787	87-010-184-080		C-CAP,S 3300P-50 B
C788	87-010-184-080		C-CAP,S 3300P-50 B
C789	87-010-179-080		C-CAP,S 1200P-50 B
C790	87-010-179-080		C-CAP,S 1200P-50 B
C791	87-010-401-080		CAP,E 1-50 SME
C792	87-010-180-080		C-CAP,S 1500P-50 B
C793	87-010-189-080		C-CAP,S 8200P-50 B
C794	87-010-408-080		CAP,E 47-50 SME
C795	87-010-194-080		C-CAP,S 0.047-25 F
C796	87-010-403-080		CAP,E 3.3-50 SME
C797	87-010-405-080		CAP,E 10-50 SME
			<1GU,HD,LH,U,C,G>
C798	87-010-196-080		C-CAP,S 0.1-25 F
			<1GU,HD,LH,U,C,G>
C814	87-010-197-080		C-CAP,S 0.01-25 B
			<EXCEPT LH,U,C,G>

REF. NO	PART NO.	カンリ NO.	DESCRIPTION
C815	87-018-134-080		CAP,TC-U 0.01-16 Y
C817	87-010-197-080		C-CAP,S 0.01-25 B
C818	87-010-197-080		C-CAP,S 0.01-25 B
C819	87-010-197-080		C-CAP,S 0.01-25 B
C820	87-010-260-080		CAP,E 47-25 SME
C821	87-010-197-080		C-CAP,S 0.01-25 B
C822	87-010-197-080		C-CAP,S 0.01-25 B
C823	87-010-197-080		C-CAP,S 0.01-25 B
C824	87-018-134-080		CAP,TC-U 0.01-16 Y
			<1GU,HD,LH,U,C,G>
C825	87-015-819-080		CHIP CAP 0.01
			<1GHE,1GHR,1GHK,1GU,HD>
C826	87-010-196-080		C-CAP,S 0.1-25 F
C827	87-010-196-080		C-CAP,S 0.1-25 F
C830	87-015-819-080		CHIP CAP 0.01
C831	87-010-197-080		C-CAP,S 0.01-25 B
C832	87-010-197-080		C-CAP,S 0.01-25 B
			<EXCEPT 1GU,HD,LH,U,C,G>
C833	87-010-197-080		C-CAP,S 0.01-25 B
			<EXCEPT 1GU,LH,U,C,G>
C835	87-010-197-080		C-CAP,S 0.01-25 B
C901	87-010-401-080		CAP,E 1-50 SME
			<1GHE,1GHR,1GHK,1GU,HD>
C902	87-010-178-080		C-CAP,S 1000P-50 B
			<1GHE,1GHR,1GHK,1GU,HD>
C903	87-010-178-080		C-CAP,S 1000P-50 B
			<1GHE,1GHR,1GHK,1GU,HD>
C904	87-010-184-080		C-CAP,S 3300P-50 B
			<1GHE,1GHR,1GHK,1GU,HD>
C905	87-010-177-080		C-CAP,S 820P-50 SL
			<1GHE,1GHR,1GHK,1GU,HD>
C906	87-010-178-080		C-CAP,S 1000P-50 B
			<1GHE,1GHR,1GHK,1GU,HD>
C907	87-010-185-080		C-CAP,S 3900P-50 B
			<1GHE,1GHR,1GHK,1GU,HD>
C909	87-010-175-080		C-CAP,S 560P-50 SL
			<1GHE,1GHR,1GHK,1GU,HD>
C910	87-010-176-080		C-CAP,S 680P-50 SL
			<1GHE,1GHR,1GHK,1GU,HD>
C911	87-010-196-080		C-CAP,S 0.1-25 F
			<1GHE,1GHR,1GHK,1GU,HD>
C918	87-010-186-080		C-CAP,S 4700P-50 B
			<1GHE,1GHR,1GHK,1GU,HD>
C920	87-010-408-080		CAP,E 47-50 SME
			<1GHE,1GHR,1GHK,1GU,HD>
C921	87-010-247-080		CAP,E 100-50 SME
			<1GHE,1GHR,1GHK,1GU,HD>
C922	87-010-196-080		C-CAP,S 0.1-25 F
			<1GHE,1GHR,1GHK,1GU,HD>
C923	87-010-154-080		C-CAP,S 10P-50 CH
			<1GHE,1GHR,1GHK,1GU,HD>
C924	87-010-154-080		C-CAP,S 10P-50 CH
			<1GHE,1GHR,1GHK,1GU,HD>
C925	87-018-209-080		CAP,TC-U 0.1-50 F
			<1GHE,1GHR,1GHK,1GU,HD>
C926	87-010-196-080		C-CAP,S 0.1-25 F
			<50HE,50HR,50HK,LH,U,C,G>
C927	87-010-197-080		C-CAP,S 0.01-25 B
			<1GHE,1GHR,1GHK,1GU,HD>
C945	87-012-154-080		C-CAP,S 150P-50 CH
			<1GHE,1GHR,1GHK,1GU,HD>
C947	87-010-401-080		CAP,E 1-50 SME
C949	87-010-197-080		C-CAP,S 0.01-25 B
			<1GU,HD,LH,U,C,G>
C951	87-010-401-080		CAP,E 1-50 SME
			<1GU,HD,LH,U,C,G>
C952	87-010-311-080		C-CAP,S 12P-50 CH
			<1GU,HD,LH,U,C,G>
C983	87-010-544-080		CAP,E 0.1-50<1GU,HD,LH,U,C,G>
C986	87-015-785-080		C-CAP,0.1-25 F<HD>
C986	87-010-196-080		C-CAP,S 0.1-25 F<HD>
C987	87-015-819-080		CHIP CAP 0.01
C988	87-016-247-080		C-CAP,0.1-50F
C990	87-010-197-080		C-CAP,S 0.01-25 B
			<1GU,HD,LH,U,C,G>
C993	87-010-197-080		C-CAP,S 0.01-25 B
			<EXCEPT 1GU,LH,U,C,G>
C995	87-010-197-080		C-CAP,S 0.01-25 B
C999	87-018-134-080		CAP,TC-U 0.01-16 Y
			<1GU,HD,LH,U,C,G>
CF801	87-008-261-010		FILTER,SFE10.7MA5-A
CF802	87-008-261-010		FILTER,SFE10.7MA5-A
FFE801	85-NF5-605-010		FE PACK 2 EX<EXCEPT HD>
FFE801	85-NF5-606-010		FE PACK 3 D-N<HD>
J250	87-099-678-010		JACK,6.3W/S BLK
J253	87-009-621-010		JACK,PIN 1P BLK
			<EXCEPT 1GU,U,C,G>
J253	87-099-475-010		JACK,PIN 3P BLK W/E<1GU,U,C,G>
J254	87-033-227-010		TERMINAL,SP 4P R(Z)*<EXCEPT 1GU>
J254	87-033-229-010		TERMINAL,SP 4P U<1GU>
J652	80-MT3-616-010		JACK,PIN 2P
J801	82-NF5-621-010		ANT TERM JBT0222
L403	87-007-341-010		COIL,TRAP 85K
L404	87-007-341-010		COIL,TRAP 85K
L451	87-007-336-010		COIL,OSC 85K BIAS
L701	81-631-643-010		COIL,1 POLE MPX
L702	81-631-643-010		COIL,1 POLE MPX
L741	87-006-253-010		COIL,FM.DET N
L742	81-631-612-010		CFMT 450A
			<EXCEPT 1GU,HD,LH,U,C,G>
L742	82-NT1-659-010		FILTER,CFAZ-450 2NT
			<1GU,LH,U,C,G>
L742	82-NT1-684-010		FILTER,PCFMT-060 2NT<HD>
L770	87-003-102-080		COIL,10UH
L832	87-003-098-080		COIL,2.2UH
L981	81-MX4-620-010		AM PACK 3,S<1GU,HD,LH,U,C,G>
R105	87-022-050-080		RES,M/F 0.22-1W
R106	87-022-050-080		RES,M/F 0.22-1W
R203	87-022-571-080		RES,M/F 0.33-2WJ<EXCEPT 1GU,U,C>
R204	87-022-571-080		RES,M/F 0.33-2WJ<EXCEPT 1GU,U,C>
RY101	87-045-372-010		RELAY,DH12D2-O(M)<C>
RY101	87-045-361-010		RELAY,DH12D2-OS(M)-2<EXCEPT C>
RY102	87-045-382-010		RELAY,OUAZ-SH-112L
SFR301	87-024-174-080		SFR,33K DIA6 V
SFR302	87-024-174-080		SFR,33K DIA6 V
SFR303	87-024-174-080		SFR,33K DIA6 V
SFR304	87-024-174-080		SFR,33K DIA6 V
SFR305	87-024-175-080		SFR,47K DIA6 V
SFR306	87-024-175-080		SFR,47K DIA6 V
SFR451	87-024-175-080		SFR,47K DIA6 V
SFR452	87-024-175-080		SFR,47K DIA6 V
SFR722	87-024-170-080		SFR,3.3K DIA6 V
TC701	87-011-253-080		TRIMMER,30P LAR<EXCEPT HD>
VR651	82-NF5-660-010		VR,50KBX2 RK14K12A
W101	85-NF5-628-010		F-CABLE,7P-2.5<EXCEPT HD>
W101	83-NEK-601-010		F-CABLE,7P-2.5<HD>
W102	85-NF5-617-010		CABLE,FFC 6P-1.25
X702	87-030-283-010		VIB,CER CSA3.60MGF N<HD>
X703	84-508-618-010		VIB,CER CSB 456 F15
X721	87-030-163-010		VIB,XTAL 7.2MHZ(NDK)
			<1GU,LH,U,C,G>
X721	87-030-278-080		VIB,XTAL 7.2MHZ,S
			<EXCEPT 1GU,LH,U,C,G
X722	87-030-354-010		VIB,CF BFU450C
			<EXCEPT 1GU,HD,LH,U,C,G>
X901	87-030-348-080		VIB,CER 16.0MHZ CST
			<1GHE,1GHR,1GHK,1GU,HD>

FRONT C.B

REF. NO	PART NO.	カンリ NO.	DESCRIPTION
C201	87-015-698-040		CAP,E 4.7-50 7L
C202	87-015-698-040		CAP,E 4.7-50 7L
C203	87-010-408-040		CAP,E 47-50 SME
C204	87-010-401-040		CAP,E 1-50 SME
C205	87-010-263-040		CAP,E 100-10
C206	87-010-248-040		CAP,E 220-10 SME
C207	87-015-695-040		CAP,E 1-50 7L
C208	87-015-785-080		C-CAP,0.1-25 F
C209	87-010-317-080		C-CAP,S 39P-50 CH
C210	87-010-313-080		C-CAP,S 18P-50 CH
C211	87-010-318-080		C-CAP,S 47P-50 CH
C212	87-015-681-040		CAP,E 10-16 7L
C213	87-010-196-080		C-CAP,S 0.1-25 F
C214	87-010-196-080		C-CAP,S 0.1-25 F
C215	87-015-785-080		C-CAP,0.1-25 F
C250	87-010-178-080		C-CAP,S 1000P-50 B
C381	87-010-196-080		C-CAP,S 0.1-25 F
C382	87-010-196-080		C-CAP,S 0.1-25 F
C383	87-010-196-080		C-CAP,S 0.1-25 F
C384	87-010-196-080		C-CAP,S 0.1-25 F
C389	87-010-196-080		C-CAP,S 0.1-25 F
C401	87-010-196-080		C-CAP,S 0.1-25 F
C601	87-010-196-080		C-CAP,S 0.1-25 F
C602	87-010-322-080		C-CAP,S 100P-50 CH
C605	87-010-490-040		CAP,E 0.1-50 GAS
C606	87-015-676-040		CAP,E 47-6.3 7L
C607	87-010-319-080		C-CAP,S 56P-50 CH
C608	87-010-112-040		CAP,E 100-16
C609	87-010-196-080		C-CAP,S 0.1-25 F
C610	87-012-155-080		C-CAP,S 180P-50 CH
C611	87-010-370-040		CAP,E 330-6.3 SME
C613	87-010-196-080		C-CAP,S 0.1-25 F
C630	87-010-498-040		CAP,E 10-16 GAS
C640	87-010-382-040		CAP,E 22-25 SME
C646	87-010-196-080		C-CAP,S 0.1-25 F
C651	87-010-152-080		C-CAP,S 8P-50 CH
C652	87-010-152-080		C-CAP,S 8P-50 CH
C653	87-010-426-080		C-CAP,S 0.012-25 B
C654	87-010-178-080		C-CAP,S 1000P-50 B
C657	87-010-196-080		C-CAP,S 0.1-25 F
C658	87-010-263-040		CAP,E 100-10
C659	87-010-374-040		CAP,E 47-10
C660	87-010-196-080		C-CAP,S 0.1-25 F
C661	87-010-177-080		C-CAP,S 820P-50 SL
C662	87-010-179-080		C-CAP,S 1200P-50 B
C663	87-010-544-040		CAP,E 0.1-50 SME
C664	87-012-141-080		C-CAP,S 0.22-16 F
C665	87-010-184-080		C-CAP,S 3300P-50 B
C666	87-010-426-080		C-CAP,S 0.012-25 B
C669	87-010-404-040		CAP,E 4.7-50 SME
C670	87-010-404-040		CAP,E 4.7-50 SME
C671	87-010-182-089		C-CAP,S 2200P-50 B
FL101	85-NF6-601-010		FL,BJ362GK
J601	82-NF7-630-010		JACK,3.5 MO
J621	82-NF7-630-010		JACK,3.5 MO
L650	87-005-487-080		COIL,150UH J FLR50
LED401	87-017-784-080		LED,SEL1550CM TP8
LED402	87-017-784-080		LED,SEL1550CM TP8
LED403	87-017-784-080		LED,SEL1550CM TP8
LED404	87-017-784-080		LED,SEL1550CM TP8
LED405	87-017-784-080		LED,SEL1550CM TP8
LED406	87-017-784-080		LED,SEL1550CM TP8
LED407	87-017-731-080		LED,SEL1510CM2
LED408	87-017-731-080		LED,SEL1510CM2
LED409	87-017-731-080		LED,SEL1510CM2
LED410	87-017-731-080		LED,SEL1510CM2
LED411	87-017-731-080		LED,SEL1510CM2
LED412	87-017-731-080		LED,SEL1510CM2
LED413	87-017-731-080		LED,SEL1510CM2
LED414	87-017-731-080		LED,SEL1510CM2
LED420	87-070-201-080		LED,SLP9118C-51-S-T1
LED421	87-070-201-080		LED,SLP9118C-51-S-T1
LED422	87-070-201-080		LED,SLP9118C-51-S-T1
LED423	87-070-201-080		LED,SLP9118C-51-S-T1
LED424	87-070-278-010		LED,SLZ-738A-24-S
LED425	87-070-290-010		LED,SLZ936C-30-S
LED426	87-070-278-010		LED,SLZ-738A-24-S
LED427	87-070-278-010		LED,SLZ-738A-24-S
LED428	87-070-290-010		LED,SLZ936C-30-S
LED429	87-070-278-010		LED,SLZ-738A-24-S
S301	87-036-215-080		SW,TACT EVQ-21404M
S302	87-036-215-080		SW,TACT EVQ-21404M
S303	87-036-215-080		SW,TACT EVQ-21404M
S304	87-036-215-080		SW,TACT EVQ-21404M
S305	87-036-215-080		SW,TACT EVQ-21404M
S306	87-036-215-080		SW,TACT EVQ-21404M <1GHE,1GHR,1GHK,1GU,HD>
S307	87-036-215-080		SW,TACT EVQ-21404M <1GHE,1GHR,1GHK,1GU,HD>
S321	87-036-215-080		SW,TACT EVQ-21404M
S322	87-036-215-080		SW,TACT EVQ-21404M
S323	87-036-215-080		SW,TACT EVQ-21404M
S324	87-036-215-080		SW,TACT EVQ-21404M
S325	87-036-215-080		SW,TACT EVQ-21404M
S326	87-036-215-080		SW,TACT EVQ-21404M
S327	87-036-215-080		SW,TACT EVQ-21404M
S328	87-036-215-080		SW,TACT EVQ-21404M
S329	87-036-215-080		SW,TACT EVQ-21404M
S330	87-036-215-080		SW,TACT EVQ-21404M
S331	87-036-215-080		SW,TACT EVQ-21404M
S332	87-036-215-080		SW,TACT EVQ-21404M
S341	87-036-215-080		SW,TACT EVQ-21404M
S342	87-036-215-080		SW,TACT EVQ-21404M
S343	87-036-215-080		SW,TACT EVQ-21404M
S344	87-036-215-080		SW,TACT EVQ-21404M
S345	87-036-215-080		SW,TACT EVQ-21404M
S346	87-036-215-080		SW,TACT EVQ-21404M
S347	87-036-215-080		SW,TACT EVQ-21404M
VR601	82-NK7-616-010		VR,10KB RK11K1130
VR602	82-NK7-615-010		VR,10KA RK11K1130
W130	82-NF7-647-010		CABLE,FFC,13P-1.25 <50HE,50HR,50HK,LH,U,C,G>
W130	82-NF5-651-010		CABLE,FFC,14P-1.25 <1GHE,1GHR,1GHK,1GU,HD>
W501	85-NF5-615-010		CABLE,FFC 15P-1.25
X201	87-030-376-080		VIB,CER CSA5.76MG200
MVR C.B			
C701	87-010-181-080		C-CAP,S 1800P-50 B
C702	87-010-181-080		C-CAP,S 1800P-50 B
C703	87-010-404-040		CAP,E 4.7-50 SME
C704	87-010-404-040		CAP,E 4.7-50 SME
C705	87-010-194-080		C-CAP,S 0.047-25 F
C706	87-010-194-080		C-CAP,S 0.047-25 F
C707	87-010-186-080		C-CAP,S 4700P-50 B
C708	87-010-186-080		C-CAP,S 4700P-50 B
C709	87-010-195-080		C-CAP,S 0.068-25 F
C710	87-010-195-080		C-CAP,S 0.068-25 F
C711	87-010-405-040		CAP,E 10-50 SME
C712	87-010-405-040		CAP,E 10-50 SME
C713	87-010-380-040		CAP,E 47-16 SME
C714	87-010-370-040		CAP,E 330-6.3 SME
C715	87-010-545-040		CAP,E 0.22-50 SME
C716	87-010-545-040		CAP,E 0.22-50 SME
C719	87-010-380-040		CAP,E 47-16 SME
C721	87-010-198-080		C-CAP,S 0.022-25 B
MVR741	85-NF6-608-010		VR,50KBX2 W/S (M)

REF. NO	PART NO.	カンリ NO.	DESCRIPTION
KEY C.B			
S349	87-036-215-080		SW,TACT EVQ-21404M
S350	87-036-215-080		SW,TACT EVQ-21404M
S351	87-036-215-080		SW,TACT EVQ-21404M
S352	87-036-215-080		SW,TACT EVQ-21404M
S353	87-036-215-080		SW,TACT EVQ-21404M
W301	83-NF8-613-010		F-CABLE,2P-2.0 KEY
AC2 C.B			
R101	87-022-050-080		RES,M/F 0.22-1W
R102	87-022-050-080		RES,M/F 0.22-1W
PT C.B			
⚠	82-304-743-010		TERMINAL,1P
⚠	87-033-213-010		CLAMP,FUSE<C>
⚠	87-033-147-010		CLAMP,FUSE<EXCEPT 1GU,U,C>
⚠F101	87-035-365-010		FUSE,2A 250V T E <EXCEPT 1GU,HD,U,C>
⚠F101	87-035-414-010		FUSE,T2A 250V UL<C>
⚠PT101	85-NF6-611-010		PT,5NF-6 C<C>
⚠PT101	85-NF6-609-010		PT,5NF-6 HD<HD>
⚠PT101	85-NF6-604-010		PT,5NF-6 HR <1GHE,1GHK,50HE,50HK,LH,G>
⚠PT101	85-NF6-610-010		PT,5NF-6 HR<1GHR,50HR>
⚠PT101	85-NF6-606-010		PT,5NF-6 U<1GU,U>
⚠SW101	87-036-388-010		SW,SL 1-2-2<HD>
⚠SW101	87-036-387-010		SW,SL 1-2-3<EXCEPT 1GU,HD,U,C,G>
DECK C.B			
SFR1	87-024-581-010		SFR,3.3K DIA 6H
SOL1	82-ZM1-618-310		SOL ASSY,27
SOL2	82-ZM1-618-310		SOL ASSY,27
SW1	87-036-378-010		SW,PUSH 1-1-1 SH2
SW2	87-036-378-010		SW,PUSH 1-1-1 SH2
SW3	87-036-378-010		SW,PUSH 1-1-1 SH2
SW4	87-036-378-010		SW,PUSH 1-1-1 SH2
SW5	87-036-378-010		SW,PUSH 1-1-1 SH2
SW6	87-036-378-010		SW,PUSH 1-1-1 SH2
SW8	87-036-378-010		SW,PUSH 1-1-1 SH2
RELAY-1 C.B			
W106	85-MA2-615-019		CONN ASSY 3P PH
RELAY-2 C.B			
W105	83-NEG-608-019		CONN ASSY 8P-RPB
S.WAVE C.B<EXCEPT 1GU,HD,LH,U,C,G>			
C951	87-010-197-089		C-CAP,S 0.01-25 B <EXCEPT 1GU,HD,LH,U,C,G>
C952	87-010-197-089		C-CAP,S 0.01-25 B <EXCEPT 1GU,HD,LH,U,C,G>
C953	87-010-197-089		C-CAP,S 0.01-25 B <EXCEPT 1GU,HD,LH,U,C,G>
C954	87-010-263-089		CAP,E 100-10 <EXCEPT 1GU,HD,LH,U,C,G>
C955	87-010-154-089		C-CAP,S 10P-50 CH <EXCEPT 1GU,HD,LH,U,C,G>
C956	87-010-197-089		C-CAP,S 0.01-25 B <EXCEPT 1GU,HD,LH,U,C,G>
C957	87-010-197-089		C-CAP,S 0.01-25 B <EXCEPT 1GU,HD,LH,U,C,G>
C958	87-010-197-089		C-CAP,S 0.01-25 B <EXCEPT 1GU,HD,LH,U,C,G>
C959	87-010-544-089		CAP,E 0.1-50 <EXCEPT 1GU,HD,LH,U,C,G>
C961	87-014-051-089		CAP,PP 560P-100 J <EXCEPT 1GU,HD,LH,U,C,G>
C962	87-014-073-089		CAP,PP 4700P-100 J <EXCEPT 1GU,HD,LH,U,C,G>
C963	87-010-312-089		C-CAP,S 15P-50 CH <EXCEPT 1GU,HD,LH,U,C,G>
C964	87-010-314-089		C-CAP,S 22P-50 CH <EXCEPT 1GU,HD,LH,U,C,G>
C965	87-010-186-089		C-CAP,S 4700P-50 B <EXCEPT 1GU,HD,LH,U,C,G>
C966	87-010-263-089		CAP,E 100-10 <EXCEPT 1GU,HD,LH,U,C,G>
C970	87-010-197-089		C-CAP,S 0.01-25 B <EXCEPT 1GU,HD,LH,U,C,G>
C971	87-010-197-089		C-CAP,S 0.01-25 B <EXCEPT 1GU,HD,LH,U,C,G>
C974	87-010-196-089		C-CAP,S 0.1-25 F <EXCEPT 1GU,HD,LH,U,C,G>
C976	87-010-400-089		CAP,E 0.47-50 SME <EXCEPT 1GU,HD,LH,U,C,G>
D958	87-017-568-089		VARI-CAP,SVC 342 M/L <EXCEPT 1GU,HD,LH,U,C,G>
L951	87-006-316-019		COIL,ANT MW(SGB) <EXCEPT 1GU,HD,LH,U,C,G>
L952	87-006-255-019		COIL,ANT SW1(SG7) <EXCEPT 1GU,HD,LH,U,C,G>
L953	87-006-256-019		COIL,ANT SW2(SG7) <EXCEPT 1GU,HD,LH,U,C,G>
L954	87-005-372-089		COIL,S 1MMH TAPG <EXCEPT 1GU,HD,LH,U,C,G>
L955	87-005-372-089		COIL,S 1MMH TAPG <EXCEPT 1GU,HD,LH,U,C,G>
L956	87-007-326-019		COIL,OSC MW(SG) <EXCEPT 1GU,HD,LH,U,C,G>
L957	87-007-327-019		COIL,OSC SW1(SG) <EXCEPT 1GU,HD,LH,U,C,G>
L958	87-007-332-019		COIL,OSC SW2(SG7) <EXCEPT 1GU,HD,LH,U,C,G>
TC951	87-011-220-089		CAP,TRIMMER 20P VCT <EXCEPT 1GU,HD,LH,U,C,G>
TC952	87-011-221-089		TRIMMER,30P VCT51 <EXCEPT 1GU,HD,LH,U,C,G>
TC953	87-011-221-089		TRIMMER,30P VCT51 <EXCEPT 1GU,HD,LH,U,C,G>

TRANSISTOR ILLUSTRATION



2SA933
2SA952
2SA1296
2SA1318
2SC1815
2SC2001


2SC3266
2SC3331
2SD655
KTA1266
KTC3198




2SC1740
DTA114YS
DTA144ES



2SK365




2SD2005




2SA1162
2SC2712
2SC2714
2SC3326

DTA143EK
DTA144EK
DTA144WK
DTC114EK
DTC114YK




2SK543




2SB1370

○ チップ抵抗部品コード／CHIP RESISTOR PART CODE


チップ抵抗部品コードの成り立ち
Chip Resistor Part Coading




チップ抵抗
Chip resistor

Wattage 容量	Type 種類	Tolerance 許容誤差	Symbol 記号	Dimensions／寸法 (mm) Form／外形	L	W	t	Resistor Code: A 抵抗コード ：A
1／32W	1608	±5%	CJ		1.6	0.8	0.35	108
1／10W	2125	±5%	CJ		2	1.25	1.45	118
1／8W	3216	±5%	CJ		3.2	1.6	0.5 ~0.7	128

BLOCK DIAGRAM-1 (MAIN／FRONT)




BLOCK DIAGRAM-2 (TUNER: HE, HR, HK)




IC BLOCK DIAGRAM-1


IC, HA12185NT




IC, M65840FP




IC, M65846FP-600D




WIRING-1 (MAIN: HE, HR, HK)




SCHEMATIC DIAGRAM-1 (MAIN: HE, HR, HK)



A MAIN C.B (HE, HR, HK)
S.WAVE C.B
PT C.B
AC2 C.B
RELAY-2 C.B
RELAY-1 C.B
TO B FRONT C.B
PIN101
SIGNAL
AM/REC
FM/PB
SW1/SW2
AC120/220-230/240V 50/60Hz
TRANSISTOR OPERATION(AM FOR S WAVE C.B)
AGC BUFFER
AGC SWITCH
AM SWITCH
BAND SWITCH
SUPPLY
Q051 2SC2712
Q052 DTC114
Q053, 054, 056 2SK962
Q055 2SA1213
Q205, 204 2SC2712
Q206 2SK2225
Q207 2SC2712
Q208 DTC114
Q209 2SC2712
Q210 DTC114
Q211 2SC2712
Q212 DTA114
Q213 2SC2712
Q214 2SC2712
Q215 2SC2712
Q216 2SC2712
Q217 2SC2712
Q218 2SC2712
Q219 2SC2712
Q220 2SC2712
Q221 2SC2712
Q222 2SC2712
Q223 2SC2712
Q224 2SC2712
Q225 2SC2712
Q226 2SC2712
Q227 2SC2712
Q228 2SC2712
Q229 2SC2712
Q230 2SC2712
Q231 2SC2712
Q232 2SC2712
Q233 2SC2712
Q234 2SC2712
Q235 2SC2712
Q236 2SC2712
Q237 2SC2712
Q238 2SC2712
Q239 2SC2712
Q240 2SC2712
Q241 2SC2712
Q242 2SC2712
Q243 2SC2712
Q244 2SC2712
Q245 2SC2712
Q246 2SC2712
Q247 2SC2712
Q248 2SC2712
Q249 2SC2712
Q250 2SC2712
Q251 2SC2712
Q252 2SC2712
Q253 2SC2712
Q254 2SC2712
Q255 2SC2712
Q256 2SC2712
Q257 2SC2712
Q258 2SC2712
Q259 2SC2712
Q260 2SC2712
Q261 2SC2712
Q262 2SC2712
Q263 2SC2712
Q264 2SC2712
Q265 2SC2712
Q266 2SC2712
Q267 2SC2712
Q268 2SC2712
Q269 2SC2712
Q270 2SC2712
Q271 2SC2712
Q272 2SC2712
Q273 2SC2712
Q274 2SC2712
Q275 2SC2712
Q276 2SC2712
Q277 2SC2712
Q278 2SC2712
Q279 2SC2712
Q280 2SC2712
Q281 2SC2712
Q282 2SC2712
Q283 2SC2712
Q284 2SC2712
Q285 2SC2712
Q286 2SC2712
Q287 2SC2712
Q288 2SC2712
Q289 2SC2712
Q290 2SC2712
Q291 2SC2712
Q292 2SC2712
Q293 2SC2712
Q294 2SC2712
Q295 2SC2712
Q296 2SC2712
Q297 2SC2712
Q298 2SC2712
Q299 2SC2712
Q300 2SC2712
Q301 2SC2712
Q302 2SC2712
Q303 2SC2712
Q304 2SC2712
Q305 2SC2712
Q306 2SC2712
Q307 2SC2712
Q308 2SC2712
Q309 2SC2712
Q310 2SC2712
Q311 2SC2712
Q312 2SC2712
Q313 2SC2712
Q314 2SC2712
Q315 2SC2712
Q316 2SC2712
Q317 2SC2712
Q318 2SC2712
Q319 2SC2712
Q320 2SC2712
Q321 2SC2712
Q322 2SC2712
Q323 2SC2712
Q324 2SC2712
Q325 2SC2712
Q326 2SC2712
Q327 2SC2712
Q328 2SC2712
Q329 2SC2712
Q330 2SC2712
Q331 2SC2712
Q332 2SC2712
Q333 2SC2712
Q334 2SC2712
Q335 2SC2712
Q336 2SC2712
Q337 2SC2712
Q338 2SC2712
Q339 2SC2712
Q340 2SC2712
Q341 2SC2712
Q342 2SC2712
Q343 2SC2712
Q344 2SC2712
Q345 2SC2712
Q346 2SC2712
Q347 2SC2712
Q348 2SC2712
Q349 2SC2712
Q350 2SC2712
Q351 2SC2712
Q352 2SC2712
Q353 2SC2712
Q354 2SC2712
Q355 2SC2712
Q356 2SC2712
Q357 2SC2712
Q358 2SC2712
Q359 2SC2712
Q360 2SC2712
Q361 2SC2712
Q362 2SC2712
Q363 2SC2712
Q364 2SC2712
Q365 2SC2712
Q366 2SC2712
Q367 2SC2712
Q368 2SC2712
Q369 2SC2712
Q370 2SC2712
Q371 2SC2712
Q372 2SC2712
Q373 2SC2712
Q374 2SC2712
Q375 2SC2712
Q376 2SC2712
Q377 2SC2712
Q378 2SC2712
Q379 2SC2712
Q380 2SC2712
Q381 2SC2712
Q382 2SC2712
Q383 2SC2712
Q384 2SC2712
Q385 2SC2712
Q386 2SC2712
Q387 2SC2712
Q388 2SC2712
Q389 2SC2712
Q390 2SC2712
Q391 2SC2712
Q392 2SC2712
Q393 2SC2712
Q394 2SC2712
Q395 2SC2712
Q396 2SC2712
Q397 2SC2712
Q398 2SC2712
Q399 2SC2712
Q400 2SC2712
Q401 2SC2712
Q402 2SC2712
Q403 2SC2712
Q404 2SC2712
Q405 2SC2712
Q406 2SC2712
Q407 2SC2712
Q408 2SC2712
Q409 2SC2712
Q410 2SC2712
Q411 2SC2712
Q412 2SC2712
Q413 2SC2712
Q414 2SC2712
Q415 2SC2712
Q416 2SC2712
Q417 2SC2712
Q418 2SC2712
Q419 2SC2712
Q420 2SC2712
Q421 2SC2712
Q422 2SC2712
Q423 2SC2712
Q424 2SC2712
Q425 2SC2712
Q426 2SC2712
Q427 2SC2712
Q428 2SC2712
Q429 2SC2712
Q430 2SC2712
Q431 2SC2712
Q432 2SC2712
Q433 2SC2712
Q434 2SC2712
Q435 2SC2712
Q436 2SC2712
Q437 2SC2712
Q438 2SC2712
Q439 2SC2712
Q440 2SC2712
Q441 2SC2712
Q442 2SC2712
Q443 2SC2712
Q444 2SC2712
Q445 2SC2712
Q446 2SC2712
Q447 2SC2712
Q448 2SC2712
Q449 2SC2712
Q450 2SC2712
Q451 2SC2712
Q452 2SC2712
Q453 2SC2712
Q454 2SC2712
Q455 2SC2712
Q456 2SC2712
Q457 2SC2712
Q458 2SC2712
Q459 2SC2712
Q460 2SC2712
Q461 2SC2712
Q462 2SC2712
Q463 2SC2712
Q464 2SC2712
Q465 2SC2712
Q466 2SC2712
Q467 2SC2712
Q468 2SC2712
Q469 2SC2712
Q470 2SC2712
Q471 2SC2712
Q472 2SC2712
Q473 2SC2712
Q474 2SC2712
Q475 2SC2712
Q476 2SC2712
Q477 2SC2712
Q478 2SC2712
Q479 2SC2712
Q480 2SC2712
Q481 2SC2712
Q482 2SC2712
Q483 2SC2712
Q484 2SC2712
Q485 2SC2712
Q486 2SC2712
Q487 2SC2712
Q488 2SC2712
Q489 2SC2712
Q490 2SC2712
Q491 2SC2712
Q492 2SC2712
Q493 2SC2712
Q494 2SC2712
Q495 2SC2712
Q496 2SC2712
Q497 2SC2712
Q498 2SC2712
Q499 2SC2712
Q500 2SC2712
Q501 2SC2712
Q502 2SC2712
Q503 2SC2712
Q504 2SC2712
Q505 2SC2712
Q506 2SC2712
Q507 2SC2712
Q508 2SC2712
Q509 2SC2712
Q510 2SC2712
Q511 2SC2712
Q512 2SC2712
Q513 2SC2712
Q514 2SC2712
Q515 2SC2712
Q516 2SC2712
Q517 2SC2712
Q518 2SC2712
Q519 2SC2712
Q520 2SC2712
Q521 2SC2712
Q522 2SC2712
Q523 2SC2712
Q524 2SC2712
Q525 2SC2712
Q526 2SC2712
Q527 2SC2712
Q528 2SC2712
Q529 2SC2712
Q530 2SC2712
Q531 2SC2712
Q532 2SC2712
Q533 2SC2712
Q534 2SC2712
Q535 2SC2712
Q536 2SC2712
Q537 2SC2712
Q538 2SC2712
Q539 2SC2712
Q540 2SC2712
Q541 2SC2712
Q542 2SC2712
Q543 2SC2712
Q544 2SC2712
Q545 2SC2712
Q546 2SC2712
Q547 2SC2712
Q548 2SC2712
Q549 2SC2712
Q550 2SC2712
Q551 2SC2712
Q552 2SC2712
Q553 2SC2712
Q554 2SC2712
Q555 2SC2712
Q556 2SC2712
Q557 2SC2712
Q558 2SC2712
Q559 2SC2712
Q560 2SC2712
Q561 2SC2712
Q562 2SC2712
Q563 2SC2712
Q564 2SC2712
Q565 2SC2712
Q566 2SC2712
Q567 2SC2712
Q568 2SC2712
Q569 2SC2712
Q570 2SC2712
Q571 2SC2712
Q572 2SC2712
Q573 2SC2712
Q574 2SC2712
Q575 2SC2712
Q576 2SC2712
Q577 2SC2712
Q578 2SC2712
Q579 2SC2712
Q580 2SC2712
Q581 2SC2712
Q582 2SC2712
Q583 2SC2712
Q584 2SC2712
Q585 2SC2712
Q586 2SC2712
Q587 2SC2712
Q588 2SC2712
Q589 2SC2712
Q590 2SC2712
Q591 2SC2712
Q592 2SC2712
Q593 2SC2712
Q594 2SC2712
Q595 2SC2712
Q596 2SC2712
Q597 2SC2712
Q598 2SC2712
Q599 2SC2712
Q600 2SC2712
Q601 2SC2712
Q602 2SC2712
Q603 2SC2712
Q604 2SC2712
Q605 2SC2712
Q606 2SC2712
Q607 2SC2712
Q608 2SC2712
Q609 2SC2712
Q610 2SC2712
Q611 2SC2712
Q612 2SC2712
Q613 2SC2712
Q614 2SC2712
Q615 2SC2712
Q616 2SC2712
Q617 2SC2712
Q618 2SC2712
Q619 2SC2712
Q620 2SC2712
Q621 2SC2712
Q622 2SC2712
Q623 2SC2712
Q624 2SC2712
Q625 2SC2712
Q626 2SC2712
Q627 2SC2712
Q628 2SC2712
Q629 2SC2712
Q630 2SC2712
Q631 2SC2712
Q632 2SC2712
Q633 2SC2712
Q634 2SC2712
Q635 2SC2712
Q636 2SC2712
Q637 2SC2712
Q638 2SC2712
Q639 2SC2712
Q640 2SC2712
Q641 2SC2712
Q642 2SC2712
Q643 2SC2712
Q644 2SC2712
Q645 2SC2712
Q646 2SC2712
Q647 2SC2712
Q648 2SC2712
Q649 2SC2712
Q650 2SC2712
Q651 2SC2712
Q652 2SC2712
Q653 2SC2712
Q654 2SC2712
Q655 2SC2712
Q656 2SC2712
Q657 2SC2712
Q658 2SC2712
Q659 2SC2712
Q660 2SC2712
Q661 2SC2712
Q662 2SC2712
Q663 2SC2712
Q664 2SC2712
Q665 2SC2712
Q666 2SC2712
Q667 2SC2712
Q668 2SC2712
Q669 2SC2712
Q670 2SC2712
Q671 2SC2712
Q672 2SC2712
Q673 2SC2712
Q674 2SC2712
Q675 2SC2712
Q676 2SC2712
Q677 2SC2712
Q678 2SC2712
Q679 2SC2712
Q680 2SC2712
Q681 2SC2712
Q682 2SC2712
Q683 2SC2712
Q684 2SC2712
Q685 2SC2712
Q686 2SC2712
Q687 2SC2712
Q688 2SC2712
Q689 2SC2712
Q690 2SC2712
Q691 2SC2712
Q692 2SC2712
Q693 2SC2712
Q694 2SC2712
Q695 2SC2712
Q696 2SC2712
Q697 2SC2712
Q698 2SC2712
Q699 2SC2712
Q700 2SC2712
Q701 2SC2712
Q702 2SC2712
Q703 2SC2712
Q704 2SC2712
Q705 2SC2712
Q706 2SC2712
Q707 2SC2712
Q708 2SC2712
Q709 2SC2712
Q710 2SC2712
Q711 2SC2712
Q712 2SC2712
Q713 2SC2712
Q714 2SC2712
Q715 2SC2712
Q716 2SC2712
Q717 2SC2712
Q718 2SC2712
Q719 2SC2712
Q720 2SC2712
Q721 2SC2712
Q722 2SC2712
Q723 2SC2712
Q724 2SC2712
Q725 2SC2712
Q726 2SC2712
Q727 2SC2712
Q728 2SC2712
Q729 2SC2712
Q730 2SC2712
Q731 2SC2712
Q732 2SC2712
Q733 2SC2712
Q734 2SC2712
Q735 2SC2712
Q736 2SC2712
Q737 2SC2712
Q738 2SC2712
Q739 2SC2712
Q740 2SC2712
Q741 2SC2712
Q742 2SC2712
Q743 2SC2712
Q744 2SC2712
Q745 2SC2712
Q746 2SC2712
Q747 2SC2712
Q748 2SC2712
Q749 2SC2712
Q750 2SC2712
Q751 2SC2712
Q752 2SC2712
Q753 2SC2712
Q754 2SC2712
Q755 2SC2712
Q756 2SC2712
Q757 2SC2712
Q758 2SC2712
Q759 2SC2712
Q760 2SC2712
Q761 2SC2712
Q762 2SC2712
Q763 2SC2712
Q764 2SC2712
Q765 2SC2712
Q766 2SC2712
Q767 2SC2712
Q768 2SC2712
Q769 2SC2712
Q770 2SC2712
Q771 2SC2712
Q772 2SC2712
Q773 2SC2712
Q774 2SC2712
Q775 2SC2712
Q776 2SC2712
Q777 2SC2712
Q778 2SC2712
Q779 2SC2712
Q780 2SC2712
Q781 2SC2712
Q782 2SC2712
Q783 2SC2712
Q784 2SC2712
Q785 2SC2712
Q786 2SC2712
Q787 2SC2712
Q788 2SC2712
Q789 2SC2712
Q790 2SC2712
Q791 2SC2712
Q792 2SC2712
Q793 2SC2712
Q794 2SC2712
Q795 2SC2712
Q796 2SC2712
Q797 2SC2712
Q798 2SC2712
Q799 2SC2712
Q800 2SC2712
Q801 2SC2712
Q802 2SC2712
Q803 2SC2712
Q804 2SC2712
Q805 2SC2712
Q806 2SC2712
Q807 2SC2712
Q808 2SC2712
Q809 2SC2712
Q810 2SC2712
Q811 2SC2712
Q812 2SC2712
Q813 2SC2712
Q814 2SC2712
Q815 2SC2712
Q816 2SC2712
Q817 2SC2712
Q818 2SC2712
Q819 2SC2712
Q820 2SC2712
Q821 2SC2712
Q822 2SC2712
Q823 2SC2712
Q824 2SC2712
Q825 2SC2712
Q826 2SC2712
Q827 2SC2712
Q828 2SC2712
Q829 2SC2712
Q830 2SC2712
Q831 2SC2712
Q832 2SC2712
Q833 2SC2712
Q834 2SC2712
Q835 2SC2712
Q836 2SC2712
Q837 2SC2712
Q838 2SC2712
Q839 2SC2712
Q840 2SC2712
Q841 2SC2712
Q842 2SC2712
Q843 2SC2712
Q844 2SC2712
Q845 2SC2712
Q846 2SC2712
Q847 2SC2712
Q848 2SC2712
Q849 2SC2712
Q850 2SC2712
Q851 2SC2712
Q852 2SC2712
Q853 2SC2712
Q854 2SC2712
Q855 2SC2712
Q856 2SC2712
Q857 2SC2712
Q858 2SC2712
Q859 2SC2712
Q860 2SC2712
Q861 2SC2712
Q862 2SC2712
Q863 2SC2712
Q864 2SC2712
Q865 2SC2712
Q866 2SC2712
Q867 2SC2712
Q868 2SC2712
Q869 2SC2712
Q870 2SC2712
Q871 2SC2712
Q872 2SC2712
Q873 2SC2712
Q874 2SC2712
Q875 2SC2712
Q876 2SC2712
Q877 2SC2712
Q878 2SC2712
Q879 2SC2712
Q880 2SC2712
Q881 2SC2712
Q882 2SC2712
Q883 2SC2712
Q884 2SC2712
Q885 2SC2712
Q886 2SC2712
Q887 2SC2712
Q888 2SC2712
Q889 2SC2712
Q890 2SC2712
Q891 2SC2712
Q892 2SC2712
Q893 2SC2712
Q894 2SC2712
Q895 2SC2712
Q896 2SC2712
Q897 2SC2712
Q898 2SC2712
Q899 2SC2712
Q900 2SC2712
Q901 2SC2712
Q902 2SC2712
Q903 2SC2712
Q904 2SC2712
Q905 2SC2712
Q906 2SC2712
Q907 2SC2712
Q908 2SC2712
Q909 2SC2712
Q910 2SC2712
Q911 2SC2712
Q912 2SC2712
Q913 2SC2712
Q914 2SC2712
Q915 2SC2712
Q916 2SC2712
Q917 2SC2712
Q918 2SC2712
Q919 2SC2712
Q920 2SC2712
Q921 2SC2712
Q922 2SC2712
Q923 2SC2712
Q924 2SC2712
Q925 2SC2712
Q926 2SC2712
Q927 2SC2712
Q928 2SC2712
Q929 2SC2712
Q930 2SC2712
Q931 2SC2712
Q932 2SC2712
Q933 2SC2712
Q934 2SC2712
Q935 2SC2712
Q936 2SC2712
Q937 2SC2712
Q938 2SC2712
Q939 2SC2712
Q940 2SC2712
Q941 2SC2712
Q942 2SC2712
Q943 2SC2712
Q944 2SC2712
Q945 2SC2712
Q946 2SC2712
Q947 2SC2712
Q948 2SC2712
Q949 2SC2712
Q950 2SC2712
Q951 2SC2712
Q952 2SC2712
Q953 2SC2712
Q954 2SC2712
Q955 2SC2712
Q956 2SC2712
Q957 2SC2712
Q958 2SC2712
Q959 2SC2712
Q960 2SC2712
Q961 2SC2712
Q962 2SC2712
Q963 2SC2712
Q964 2SC2712
Q965 2SC2712
Q966 2SC2712
Q967 2SC2712
Q968 2SC2712
Q969 2SC2712
Q970 2SC2712
Q971 2SC2712
Q972 2SC2712
Q973 2SC2712
Q974 2SC2712
Q975 2SC2712
Q976 2SC2712
Q977 2SC2712
Q978 2SC2712
Q979 2SC2712
Q980 2SC2712
Q981 2SC2712
Q982 2SC2712
Q983 2SC2712
Q984 2SC2712
Q985 2SC2712
Q986 2SC2712
Q987 2SC2712
Q988 2SC2712
Q989 2SC2712
Q990 2SC2712
Q991 2SC2712
Q992 2SC2712
Q993 2SC2712
Q994 2SC2712
Q995 2SC2712
Q996 2SC2712
Q997 2SC2712
Q998 2SC2712
Q999 2SC2712
Q1000 2SC2712
Q1001 2SC2712
Q1002 2SC2712
Q1003 2SC2712
Q1004 2SC2712
Q1005 2SC2712
Q1006 2SC2712
Q1007 2SC2712
Q1008 2SC2712
Q1009 2SC2712
Q1010 2SC2712
Q1011 2SC2712
Q1012 2SC2712
Q1013 2SC2712
Q1014 2SC2712
Q1015 2SC2712
Q1016 2SC2712
Q1017 2SC2712
Q1018 2SC2712
Q1019 2SC2712
Q1020 2SC2712
Q1021 2SC2712
Q1022 2SC2712
Q1023 2SC2712
Q1024 2SC2712
Q1025 2SC2712
Q1026 2SC2712
Q1027 2SC2712
Q1028 2SC2712
Q1029 2SC2712
Q1030 2SC2712
Q1031 2SC2712
Q1032 2SC2712
Q1033 2SC2712
Q1034 2SC2712
Q1035 2SC2712
Q1036 2SC2712
Q1037 2SC2712
Q1038 2SC2712
Q1039 2SC2712
Q1040 2SC2712
Q1041 2SC2712
Q1042 2SC2712
Q1043 2SC2712
Q1044 2SC2712
Q1045 2SC2712
Q1046 2SC2712
Q1047 2SC2712
Q1048 2SC2712
Q1049 2SC2712
Q1050 2SC2712
Q1051 2SC2712
Q1052 2SC2712
Q1053 2SC2712
Q1054 2SC2712
Q1055 2SC2712
Q1056 2SC2712
Q1057 2SC2712
Q1058 2SC2712
Q1059 2SC2712
Q1060 2SC2712
Q1061 2SC2712
Q1062 2SC2712
Q1063 2SC2712
Q1064 2SC2712
Q1065 2SC2712
Q1066 2SC2712
Q1067 2SC2712
Q1068 2SC2712
Q1069 2SC2712
Q1070 2SC2712
Q1071 2SC2712
Q1072 2SC2712
Q1073 2SC2712
Q1074 2SC2712
Q1075 2SC2712
Q1076 2SC2712
Q1077 2SC2712
Q1078 2SC2712
Q1079 2SC2712
Q1080 2SC2712
Q1081 2SC2712
Q1082 2SC2712
Q1083 2SC2712
Q1084 2SC2712
Q1085 2SC2712
Q1086 2SC2712
Q1087 2SC2712
Q1088 2SC2712
Q1089 2SC2712
Q1090 2SC2712
Q1091 2SC2712
Q1092 2SC2712
Q1093 2SC2712
Q1094 2SC2712
Q1095 2SC2712
Q1096 2SC2712
Q1097 2SC2712
Q1098 2SC2712
Q1099 2SC2712
Q1100 2SC2712
Q1101 2SC2712
Q1102 2SC2712
Q1103 2SC2712
Q1104 2SC2712
Q1105 2SC2712
Q1106 2SC2712
Q1107 2SC2712
Q1108 2SC2712
Q1109 2SC2712
Q1110 2SC2712
Q1111 2SC2712
Q1112 2SC2712
Q1113 2SC2712
Q1114 2SC2712
Q1115 2SC2712
Q1116 2SC2712
Q1117 2SC2712
Q1118 2SC2712
Q1119 2SC2712
Q1120 2SC2712
Q1121 2SC2712
Q1122 2SC2712
Q1123 2SC2712
Q1124 2SC2712
Q1125 2SC2712
Q1126 2SC2712
Q1127 2SC2712
Q1128 2SC2712
Q1129 2SC2712
Q1130 2SC2712
Q1131 2SC2712
Q1132 2SC2712
Q1133 2SC2712
Q1134 2SC2712
Q1135 2SC2712
Q1136 2SC2712
Q1137 2SC2712
Q1138 2SC2712
Q1139 2SC2712
Q1140 2SC2712
Q1141 2SC2712
Q1142 2SC2712
Q1143 2SC2712
Q1144 2SC2712
Q1145 2SC2712
Q1146 2SC2712
Q1147 2SC2712
Q1148 2SC2712
Q1149 2SC2712
Q1150 2SC2712
Q1151 2SC2712
Q1152 2SC2712
Q1153 2SC2712
Q1154 2SC2712
Q1155 2SC2712
Q1156 2SC2712
Q1157 2SC2712
Q1158 2SC2712
Q1159 2SC2712
Q1160 2SC2712
Q1161 2SC2712
Q1162 2SC2712
Q1163 2SC2712
Q1164 2SC2712
Q1165 2SC2712
Q1166 2SC2712
Q1167 2SC2712
Q1168 2SC2712
Q1169 2SC2712
Q1170 2SC2712
Q1171 2SC2712
Q1172 2SC2712
Q1173 2SC2712
Q1174 2SC2712
Q1175 2SC2712
Q1176 2SC2712
Q1177 2SC2712
Q1178 2SC2712
Q1179 2SC2712
Q1180 2SC2712
Q1181 2SC2712
Q1182 2SC2712
Q1183 2SC2712
Q1184 2SC2712
Q1185 2SC2712
Q1186 2SC2712
Q1187 2SC2712
Q1188 2SC2712
Q1189 2SC2712
Q1190 2SC2712
Q1191 2SC2712
Q1192 2SC2712
Q1193 2SC2712
Q1194 2SC2712
Q1195 2SC2712
Q1196 2SC2712
Q1197 2SC2712
Q1198 2SC2712
Q1199 2SC2712
Q1200 2SC2712
Q1201 2SC2712
Q1202 2SC2712
Q1203 2SC2712
Q1204 2SC2712
Q1205 2SC2712
Q1206 2SC2712
Q1207 2SC2712
Q1208 2SC2712
Q1209 2SC2712
Q1210 2SC2712
Q1211 2SC2712
Q1212 2SC2712
Q1213 2SC2712
Q1214 2SC2712
Q1215 2SC2712
Q1216 2SC2712
Q1217 2SC2712
Q1218 2SC2712
Q1219 2SC2712
Q1220 2SC2712
Q1221 2SC2712
Q1222 2SC2712
Q1223 2SC2712
Q1224 2SC2712
Q1225 2SC2712
Q1226 2SC2712
Q1227 2SC2712
Q1228 2SC2712
Q1229 2SC2712
Q1230 2SC2712
Q1231 2SC2712
Q1232 2SC2712
Q1233 2SC2712
Q1234 2SC2712
Q1235 2SC2712
Q1236 2SC2712
Q1237 2SC2712
Q1238 2SC2712
Q1239 2SC2712
Q1240 2SC2712
Q1241 2SC2712
Q1242 2SC2712
Q1243 2SC2712
Q1244 2SC2712
Q1245 2SC2712
Q1246 2SC2712
Q1247 2SC2712
Q1248 2SC2712
Q1249 2SC2712
Q1250 2SC2712
Q1251 2SC2712
Q1252 2SC2712
Q1253 2SC2712
Q1254 2SC2712
Q1255 2SC2712
Q1256 2SC2712
Q1257 2SC2712
Q1258 2SC2712
Q1259 2SC2712
Q1260 2SC2712
Q1261 2SC2712
Q1262 2SC2712
Q1263 2SC2712
Q1264 2SC2712
Q1265 2SC2712
Q1266 2SC2712
Q1267 2SC2712
Q1268 2SC2712
Q1269 2SC2712
Q1270 2SC2712
Q1271 2SC2712
Q1272 2SC2712
Q1273 2SC2712
Q1274 2SC2712
Q1275 2SC2712
Q1276 2SC2712
Q1277 2SC2712
Q1278 2SC2712
Q1279 2SC2712
Q1280 2SC2712
Q1281 2SC2712
Q1282 2SC2712
Q1283 2SC2712
Q1284 2SC2712
Q1285 2SC2712
Q1286 2SC2712
Q1287 2SC2712
Q1288 2SC2712
Q1289 2SC2712
Q1290 2SC2712
Q1291 2SC2712
Q1292 2SC2712
Q1293 2SC2712
Q1294 2SC2712
Q1295 2SC2712
Q1296 2SC2712
Q1297 2SC2712
Q1298 2SC2712
Q1299 2SC2712
Q1300 2SC2712
Q1301 2SC2712
Q1302 2SC2712
Q1303 2SC2712
Q1304 2SC2712
Q1305 2SC2712
Q1306 2SC2712
Q1307 2SC2712
Q1308 2SC2712
Q1309 2SC2712
Q1310 2SC2712
Q1311 2SC2712
Q1312 2SC2712
Q1313 2SC2712
Q1314 2SC2712
Q1315 2SC2712
Q1316 2SC2712
Q1317 2SC2712
Q1318 2SC2712
Q1319 2SC2712
Q1320 2SC2712
Q1321 2SC2712
Q1322 2SC2712
Q1323 2SC2712
Q1324 2SC2712
Q1325 2SC2712
Q1326 2SC2712
Q1327 2SC2712
Q1328 2SC2712
Q1329 2SC2712
Q1330 2SC2712
Q1331 2SC2712
Q1332 2SC2712
Q1333 2SC2712
Q1334 2SC2712
Q1335 2SC2712
Q1336 2SC2712
Q1337 2SC2712
Q1338 2SC2712
Q1339 2SC2712
Q1340 2SC2712
Q1341 2SC2712
Q1342 2SC2712
Q1343 2SC2712
Q1344 2SC2712
Q1345 2SC2712
Q1346 2SC2712
Q1347 2SC2712
Q1348 2SC2712
Q1349 2SC2712
Q1350 2SC2712
Q1351 2SC2712
Q1352 2SC2712
Q1353 2SC2712
Q1354 2SC2712
Q1355 2SC2712
Q1356 2SC2712
Q1357 2SC2712
Q1358 2SC2712
Q1359 2SC2712
Q1360 2SC2712
Q1361 2SC2712
Q1362 2SC2712
Q1363 2SC2712
Q1364 2SC2712
Q1365 2SC2712
Q1366 2SC2712
Q1367 2SC2712
Q1368 2SC2712
Q1369 2SC2712
Q1370 2SC2712
Q1371 2SC2712
Q1372 2SC2712
Q1373 2SC2712
Q1374 2SC2712
Q1375 2SC2712
Q1376 2SC2712
Q1377 2SC2712
Q1378 2SC2712
Q1379 2SC2712
Q1380 2SC2712
Q1381 2SC2712
Q1382 2SC2712
Q1383 2SC2712
Q1384 2SC2712
Q1385 2SC2712
Q1386 2SC2712
Q1387 2SC2712
Q1388 2SC2712
Q1389 2SC2712
Q1390 2SC2712
Q1391 2SC2712
Q1392 2SC2712
Q1393 2SC2712
Q1394 2SC2712
Q1395 2SC2712
Q1396 2SC2712
Q1397 2SC2712
Q1398 2SC2712
Q1399 2SC2712
Q1400 2SC2712
Q1401 2SC2712
Q1402 2SC2712
Q1403 2SC2712
Q1404 2SC2712
Q1405 2SC2712
Q1406 2SC2712
Q1407 2SC2712
Q1408 2SC2712
Q1409 2SC2712
Q1410 2SC2712
Q1411 2SC2712
Q1412 2SC2712
Q1413 2SC2712
Q1414 2SC2712
Q1415 2SC2712
Q1416 2SC2712
Q1417 2SC2712
Q1418 2SC2712
Q1419 2SC2712
Q1420 2SC2712
Q1421 2SC2712
Q1422 2SC2712
Q1423 2SC2712
Q1424 2SC2712
Q1425 2SC2712
Q1426 2SC2712
Q1427 2SC2712
Q1428 2SC2712
Q1429 2SC2712
Q1430 2SC2712
Q1431 2SC2712
Q1432 2SC2712
Q1433 2SC2712
Q1434 2SC2712
Q1435 2SC2712
Q1436 2SC2712
Q1437 2SC2712
Q1438 2SC2712
Q1439 2SC2712
Q1440 2SC2712
Q1441 2SC2712
Q1442 2SC2712
Q1443 2SC2712
Q1444 2SC2712
Q1445 2SC2712
Q1446 2SC2712
Q1447 2SC2712
Q1448 2SC2712
Q1449 2SC2712
Q1450 2SC2712
Q1451 2SC2712
Q1452 2SC2712
Q1453 2SC2712
Q1454 2SC2712
Q1455 2SC2712
Q1456 2SC2712
Q1457 2SC2712
Q1458 2SC2712
Q1459 2SC2712
Q1460 2SC2712
Q1461 2SC2712
Q1462 2SC2712
Q1463 2SC2712
Q1464 2SC2712
Q1465 2SC2712
Q1466 2SC2712
Q1467 2SC2712
Q1468 2SC2712
Q1469 2SC2712
Q1470 2SC2712
Q1471 2SC2712
Q1472 2SC2712
Q1473 2SC2712
Q1474 2SC2712
Q1475 2SC2712
Q1476 2SC2712
Q1477 2SC2712
Q1478 2SC2712
Q1479 2SC2712
Q1480 2SC2712
Q1481 2SC2712
Q1482 2SC2712
Q1483 2SC2712
Q1484 2SC2712
Q1485 2SC2712
Q1486 2SC2712
Q1487 2SC2712
Q1488 2SC2712
Q1489 2SC2712
Q1490 2SC2712
Q1491 2SC2712
Q1492 2SC2712
Q1493 2SC2712
Q1494 2SC2712
Q1495 2SC2712
Q1496 2SC2712
Q1497 2SC2712
Q1498 2SC2712
Q1499 2SC2712
Q1500 2SC2712
Q1501 2SC2712
Q1502 2SC2712
Q1503 2SC2712
Q1504 2SC2712
Q1505 2SC2712
Q1506 2SC2712
Q1507 2SC2712
Q1508 2SC2712
Q1509 2SC2712
Q1510 2SC2712
Q1511 2SC2712
Q1512 2SC2712
Q1513 2SC2712
Q1514 2SC2712
Q1515 2SC2712
Q1516 2SC2712
Q1517 2SC2712
Q1518 2SC2712
Q1519 2SC2712
Q1520 2SC2712
Q1521 2SC2712
Q1522 2SC2712
Q1523 2SC2712
Q1524 2SC2712
Q1525 2SC2712
Q1526 2SC2712
Q1527 2SC2712
Q1528 2SC2712
Q1529 2SC2712
Q1530 2SC2712
Q1531 2SC2712
Q1532 2SC2712
Q1533 2SC2712
Q1534 2SC2712
Q1535 2SC2712
Q1536 2SC2712
Q1537 2SC2712
Q1538 2SC2712
Q1539 2SC2712
Q1540 2SC2712
Q1541 2SC2712
Q1542 2SC2712
Q1543 2SC2712
Q1544 2SC2712
Q1545 2SC2712
Q1546 2SC2712
Q1547 2SC2712
Q1548 2SC2712
Q1549 2SC2712
Q1550 2SC2712
Q1551 2SC2712
Q1552 2SC2712
Q1553 2SC2712
Q1554 2SC2712
Q1555 2SC2712
Q1556 2SC2712
Q1557 2SC2712
Q1558 2SC2712
Q1559 2SC2712
Q1560 2SC2712
Q1561 2SC2712
Q1562 2SC2712
Q1563 2SC2712
Q1564 2SC2712
Q1565 2SC2712
Q1566 2SC2712
Q1567 2SC2712
Q1568 2SC2712
Q1569 2SC2712
Q1570 2SC2712
Q1571 2SC2712
Q1572 2SC2712
Q1573 2SC2712
Q1574 2SC2712
Q1575 2SC2712
Q1576 2SC2712
Q1577 2SC2712
Q1578 2SC2712
Q1579 2SC2712
Q1580 2SC2712
Q1581 2SC2712
Q1582 2SC2712
Q1583 2SC2712
Q1584 2SC2712
Q1585 2SC2712
Q1586 2SC2712
Q1587 2SC2712
Q1588 2SC2712
Q1589 2SC2712
Q1590 2SC2712
Q1591 2SC2712
Q1592 2SC2712
Q1593 2SC2712
Q1594 2SC2712
Q1595 2SC2712
Q1596 2SC2712
Q1597 2SC2712
Q1598 2SC2712
Q1599 2SC2712
Q1600 2SC2712
Q1601 2SC2712
Q1602 2SC2712
Q1603 2SC2712
Q1604 2SC2712
Q1605 2SC2712
Q1606 2SC2712
Q1607 2SC2712
Q1608 2SC2712
Q1609 2SC2712
Q1610 2SC2712
Q1611 2SC2712
Q1612 2SC2712
Q1613 2SC2712
Q1614 2SC2712
Q1615 2SC2712
Q1616 2SC2712
Q1617 2SC2712
Q1618 2SC2712
Q1619 2SC2712
Q1620 2SC2712
Q1621 2SC2712
Q1622 2SC2712
Q1623 2SC2712
Q1624 2SC2712
Q1625 2SC2712
Q1626 2SC2712
Q1627 2SC2712
Q1628 2SC2712
Q1629 2SC2712
Q1630 2SC2712
Q1631 2SC2712
Q1632 2SC2712
Q1633 2SC2712
Q1634 2SC2712
Q1635 2SC2712
Q1636 2SC2712
Q1637 2SC2712
Q1638 2SC2712
Q1639 2SC2712
Q1640 2SC2712
Q1641 2SC2712
Q1642 2SC2712
Q1643 2SC2712
Q1644 2SC2712
Q1645 2SC2712
Q1646 2SC2712
Q1647 2SC2712
Q1648 2SC2712
Q1649 2SC2712
Q1650 2SC2712
Q1651 2SC2712
Q1652 2SC2712
Q1653 2SC2712
Q1654 2SC2712
Q1655 2SC2712
Q1656 2SC2712
Q1657 2SC2712
Q1658 2SC2712
Q1659 2SC2712
Q1660 2SC2712
Q1661 2SC2712
Q1662 2SC2712
Q1663 2SC2712
Q1664 2SC2712
Q1665 2SC2712
Q1666 2SC2712
Q1667 2SC2712
Q1668 2SC2712
Q1669 2SC2712
Q1670 2SC2712
Q1671 2SC2712
Q1672 2SC2712
Q1673 2SC2712
Q1674 2SC2712
Q1675 2SC2712
Q1676 2SC2712
Q1677 2SC2712
Q1678 2SC2712
Q1679 2SC2712
Q1680 2SC2712
Q1681 2SC2712
Q1682 2SC2712
Q1683 2SC2712
Q1684 2SC2712
Q1685 2SC2712
Q1686 2SC2712
Q1687 2SC2712
Q1688 2SC2712
Q1689 2SC2712
Q1690 2SC2712
Q1691 2SC2712
Q1692 2SC2712
Q1693 2SC2712
Q1694 2SC2712
Q1695 2SC2712
Q1696 2SC2712
Q1697 2SC2712
Q1698 2SC2712
Q1699 2SC2712
Q1700 2SC2712
Q1701 2SC2

BLOCK DIAGRAM-3 (TUNER: LH, U, C, G)






A MAIN C.B (LH, U, C, G)
FROM I RELAY-2 C.B
CON351
TO PIN351
FROM H RELAY-1 C.B
CON301
TO PIN301
J801 ANTENNA
AM LOOP
FM 75Ω
VR651 VIDEO/AUX INPUT LEVEL
J652 VIDEO/AUX
W102
TO CON604
LH ONLY
SURROUND SPEAKERS
SPEAKER IMP: 16Ω
J253 (2/2) SURROUND SPEAKERS
J253 SUPER WOOFER
J251 SPEAKER IMP: 6Ω SPEAKERS
J254
BLK
YEL
TO E AC2 C.B WH102
FROM B FRONT C.B
CON101
J250 PHONES
IC604
IC502
IC602
IC603
IC901
IC301
IC211
Q351
Q352
Q452
Q272
Q101
Q103
Q104
Q106
EXCEPT NV51G
NV51G ONLY
LH, G ONLY
UC ONLY

SCHEMATIC DIAGRAM-2 (MAIN: LH, U, C, G)




SCHEMATIC DIAGRAM-3 (MAIN: HD)






A MAIN C.B (HD)
FROM I RELAY-2 C.B
CON351
TO PIN351
FROM H RELAY-1 C.B
CON301
TO PIN301
J801 ANTENNA
AM LOOP
FM 75Ω
VR651 VIDEO/AUX INPUT LEVEL
J652 VIDEO/AUX
W102
TO CON604
SURROUND SPEAKERS
SPEAKER IMP:16Ω
J253 SUPER WOOFER
J251 SPEAKER IMP:16Ω SPEAKERS
J254
J255
J250 PHONES
FROM B FRONT C.B
CON101
IC901
IC602
IC603
IC502
IC72
IC60A
Q351
Q352
Q452
Q501
Q106
Q104
Q101
IC211
BLK
5
3
BLK
YEL
TO E AC2 C.B
WH102


BLOCK DIAGRAM-4 (TUNER: HD)



SCHEMATIC DIAGRAM-4 (FRONT)





B FRONT C. B
FROM C0 MECHANISM
NV51G ONLY 4Z0-1
3CD C.B
FROM D DECK C.B CON1
TO CON501
W501
TO CON104
W130
D349 PAL
D348 KEY-CON
D342 AM-ST/FM-WIDE
D345 SW
D343 AM-10K
FL101 DISPLAY
VR602 MIC MIXING
MAX. ↔ .MIN
VR601 DIGITAL ECHO
MAX. ↔ .MIN
NV51O NV50HE,HR,HK ONLY
CON501
IC201
IC380
IC402
IC401
IC403
CON104
CON701
IC650
IC602
X201
FL101
S330 HALL
S331 LIVE
S332 DISCO
S327 ROCK
S328 POP
S329 CLASSIC
S341 DEMO
S347 T-BASS
S321 POWER
W301
RED
BRN
W302
CON601
TO A MAIN C.B
J601 MIC 1
J621 MIC 2
W601
PIN701
S351 DISC 1
S350 DISC 2
S349 DISC 3
DISC DIRECT PLAY
S352 DISC CHANGE
S353 OPEN/CLOSE
D KEY C. B
MVR741 VOLUME
MAX. ↔ .MIN
C MVR C. B
NV51O ONLY
S306 KEY CONTROL UP
S307 KEY CONTROL DOWN
LED424, 425, 426
LED427, 428, 429
DECK LIGHT
LED405 S326 UP
LED406 S325 DOWN
LED403 S305 CLEAR
S323 SET
LED401, 402 S324 DIRECTION/PRESET
LED407, 408, 420 S345 CD
LED409, 410, 421 S342 TAPE (DECK 1/2)
LED411, 412, 422 S344 AUX/VIDEO
LED413, 414, 423 S343 TUNER
S346 VOCAL FADER/MULTIPLEX
S304 C0 EDIT/CHECK
S303 REV MODE (DECK 2/2)
S322 REC/REC MUTE
S302 DOLBY NR
S301 SYNC DUB NORM/HIGH




G DECK C.B

HE, HR, HK ONLY


J S.WAVE C.B




I RELAY-2 C.B



H RELAY-1 C.B




WIRING-6 (PT)


HĐ ONLY
F PT C.B
AC 100-120/200-240V
50/60HZ
F101
SW101
AC VOLTAGE
100-120V
200-240V
PT101
U,C ONLY
F PT C.B
AC 120V
60HZ
BLK
WHT LINE
U ONLY
C ONLY
PT101
R103
HE, HR, HK, LH, G
F PTC.B
HE, HK, HR, LH
AC 120V/220-230V/240V
50/60HZ
G:230/240V 50HZ
*1
EXCEPT G:BLU
G:
*2
EXCEPT G:BRN
G:
F101
SW101
120V
220-230V
240V
AC VOLTAGE
120V
220V-230V
240V
PT101
R102
R101
WH102
BLK
BLK
YEL
TO A MAIN C.B WH101
E AC2 C.B

FL DISPLAY (BJ362GK) GRID ASSIGNMENT／ANODE CONNECTION

GRID ASSIGNMENT



ANODE CONNECTION

	11G	10G	9G	8G	7G	6G	5G	4G	3G	2G	1G
P1	B10	B10	B10	C	d	d	d	d	d	s, t_{w}, x	**20**
P2	B1	B1	B1	B1	j, p	j, p	j, p	j, p	j, p	u, v_{y}, z	**19**
P3	B11	B11	B11	S8	n	n	n	n	n	3e	**18**
P4	B2	B2	B2	B2	r	r	r	r	r	3c	**17**
P5	B12	B12	B12	C	c	c	c	c	c	3a,3d,3g	**16**
P6	B3	B3	B3	B3	e	e	e	e	e	3b	**15**
P7	B13	B13	B13	O	m	m	m	m	m	2e	**14**
P8	B4	B4	B4	B4	g	g	g	g	g	2c	**13**
P9	B5	B5	B5	B5	f	f	f	f	f	2a,2d,2g	**11**
P10	B15	B15	B15	**AUTO**	b	b	b	b	b	S3	**10**
P11	B6	B6	B6	B6	k	k	k	k	k	j, m, q	**9**
P12	B16	B16	B16	B10	h	h	h	h	h	h, l, p	**8**
P13	B7	B7	B7	B7	a	a	a	a	a	k, n, r	**7**
P14	B14	B14	B14	**REC**	S7	col 3	col 1	—	**KHz**	2b	**12**
P15	B17	B17	B17	B11	S6	**DD NR**	**MONO**	((( )))	**5**	1e	**6**
P16	B8	B8	B8	B8	▷	Dp1	col 2	—	**MHz**	1a,1d,1g	**5**
P17	B18	B18	B18	B12	◁	1d	1d	1d	1d	1c	**4**
P18	B9	B9	B9	B9	**REC**	1e	1e	1e	1e	1b	**3**
P19	[ROCK]	[POP]	[CLASSIC]	B13	S5	1c	1c	1c	1c	—	**2**
P20	[DISCO]	[LIVE]	[HALL]	B14	—	1g	1g	1g	1g	S2	**1**
P21	—	—	—	[♭]	/	1f	1f	1f	1f	↺	**EDIT**
P22	**DISCO**	**LIVE**	**HALL**	♭ #	◷	1b	1b	1b	1b	**SLEEP**	**AI**
P23	**ROCK**	**POP**	**CLASSIC**	[#]	S4	1a	1a	1a	1a	**RANDOM**	**PRGM**
P24	S12	S11	S10	S9 Z	—	—	—	—	—	—	S1
P25	—	—	—	**BBE**	—	—	—	—	—	—	—

IC DESCRIPTION

IC, LC866432V-5752

Pin No.	Pin Name	I/O	Description
1	O - PLL CE	O	PLL IC chip enable .
2	O - KC / CE	O	Key control IC data latched strobe output .
3	O - M / STB	O	Main shift register data latch strobe output .
4	O - M / DATA	O	Main shift register ,PLL/Key control / DSP related data output .
5	O - M / CLK	O	Main shift register , PLL/Key control / DSP related clock .
6	O - DSPCE	O	DSP data latch strobe output .
7	$\overline{\text{RESET}}$	I	Reset input .
8	I - $\overline{\text{STEREO}}$	I	Tuner stereo detected input .
9	I - $\overline{\text{TUNE}}$ / IFC	I	Tuner $\overline{\text{SD}}$ detected input . IF count serial data input .
10	VSS1	-	GND .
11,12	CF1, 2	-	5.75MHz oscillator circuit .
13	VDD1	-	Power supply input .
14~16	I - KEY1 ~ 3	I	Key input . (A/D)
17	I - CD / SW	I	CD mechanical switch A/D converter input .
18	I - CD / DISH	I	CD turntable photo sensor A/D converter input .
19	I - MS	I	Deck music sensor signal input .
20	I - SPEANA	I	A / D input for spectrum analyzer display .
21	I - MC	I	Microphone input for auto VF display .
22	I - TM BASE	I	Reference clock input for timer watch .
23	I - $\overline{\text{HOLD}}$	I	Power failure deteched input. "L" to stop clock and maintain memory .
24	I - $\overline{\text{RMC}}$	I	System remote control signal input .
25 ~ 35	G1 ~ G11	O	FL grid output G11- G1 .
36 ~ 40	P23 ~ P19	O	FL segment output P23 ~ P19 .
41	VDD2	-	Power supply input .
42	-VP	-	Power supply input (-34.5V) for FL display .
43	P18 / $\overline{\text{CST1}}$	O / I	FL segment output P18, DECK1 cassette detect switch data input .
44	P17 / $\overline{\text{AUTO1}}$	O / I	FL segment output P17, DECK1 auto stop signal input .
45	P16 / $\overline{\text{CAM1}}$	O / I	FL segment output P16, DECK1 cam switch data input .
46	P15 / $\overline{\text{CAM2}}$	O / I	FL segment output P15, DECK2 cam switch data input .
47	P14 / $\overline{\text{AUTO2}}$	O / I	FL segment output P14, DECK2 auto stop data input .
48	P13 / $\overline{\text{CST2}}$	O / I	FL segment output P13, DECK2 cassette detect switch data input .
49	P12 / REA2	O / I	FL segment output P12, DECK2 side-A record OK switch data input .
50	P11 / REB2	O / I	FL segment output P11, DECK2 side-B record OK switch data input .
51	P10 / FM - WIDE	O / I	FL segment output P10, FM wide mode data input to diode .
52	P1 / AM - ST	O / I	FL segment output P1, AM stereo mode data input to diode .
53	P2 / AM10K	O / I	FL segment output P2, AM 10kHz step data input to diode .
54	P3 / LW	O / I	FL segment output P3, LW mode data input to diode .
55	P4 / SW	O / I	FL segment output P4, SW mode data input to diode .
56	P5 / BBE	O / I	FL segment output P5, BBE mode data input to diode .
57	P6 / DSP	O / I	FL segment output P6, DSP data input to diode .

Pin No.	Pin Name	I/O	Description
57	P6 / DSP	O / I	FL segment output P6, DSP data input to diode .
58	P7 / KEY- CON	O / I	FL segment output P7, key control data input to diode .
59	P8 / CDG	O / I	FL segment output P8, CDG data input to diode .
60	P9	O	FL segment output P9 .
61	O - CLOSE	O	CD tray close data output .
62	O - OPEN	O	CD tray open data output .
63	O - DI / R	O	CD turntable reverse rotation output .
64	O - DI / F	O	CD turntable forward rotation output.
65	O - $\overline{\text{POWER}}$	O	System power supply $\overline{\text{ON}}$ / OFF output .
66	O - $\overline{\text{SOL1}}$	O	DECK1 solenoid output .
67	O - $\overline{\text{SOL2}}$	O	DECK2 solenoid output .
68	O - $\overline{\text{MOTOR}}$	O	DECK motor output .
69	O - $\overline{\text{KEY. SCAN}}$	O	Switch scan timing output .
70	O - F / STB	O	Front shift register , data latch strobe output .
71	O - F / CLK	O	Front shift register , data transfer clock output .
72	O - F / DATA	O	Front shift register , data output .
73	VSS2	-	GND .
74	IO - BUS0	I / O	CD IC control data bus input / output .
75	IO - BUS1	I / O	CD IC control data bus input / output .
76	IO - BUS2	I / O	CD IC control data bus input / output .
77	IO - BUS3	I / O	CD IC control data bus input / output .
78	O - $\overline{\text{CCE}}$	O	CD IC control chip enable output .
79	O - CD / SQ.CLK	O	CD IC control data bus clock output .
80	O - $\overline{\text{MUTE}}$	O	System mute output .

IC, LC72131

<table>
<tr><th>Pin No.</th><th>Pin Name</th><th>I/O</th><th>Description</th></tr>
<tr><td>1</td><td>XI</td><td>–</td><td rowspan="2">A crystal oscillator (7.2MHz) is connected between these pins.</td></tr>
<tr><td>22</td><td>XO</td><td>–</td></tr>
<tr><td>2</td><td>NC</td><td>–</td><td>Not used.</td></tr>
<tr><td>3</td><td>CE</td><td>I</td><td>To enable the IC. Active "H".</td></tr>
<tr><td>4</td><td>DI</td><td>I</td><td>Digital data input from CPU (LC866432V–5751) when relevant key is operated. Active "H".</td></tr>
<tr><td>5</td><td>CLK</td><td>I</td><td>To clock in the data DI.</td></tr>
<tr><td>6</td><td>DO</td><td>O</td><td>Digital data output to CPU (LC866432V–5751).</td></tr>
<tr><td>7</td><td>TM-BASE</td><td>O</td><td>Outputs a reference clock signal (8Hz) for the clock.</td></tr>
<tr><td>8</td><td>$\overline{\text{MONO}}$/ST BEAT</td><td>O</td><td>Outputs "H" when MONO/ST BEAT is switched.</td></tr>
<tr><td>9</td><td>$\overline{\text{FM/SW1}}$</td><td>O</td><td>Output "L" or "H" as follows:
<table>
<tr><th colspan="2">2 BAND</th><th colspan="3">3 BAND</th><th colspan="4">4 BAND</th></tr>
<tr><th>AM</th><th>FM</th><th>LW</th><th>MW</th><th>FM</th><th>LW</th><th>SW1</th><th>SW2</th><th>FM</th></tr>
<tr><td>H</td><td>L</td><td>H</td><td>H</td><td>L</td><td>H</td><td>L</td><td>H</td><td>L</td></tr>
</table></td></tr>
<tr><td>10</td><td>$\overline{\text{MW/SW2}}$</td><td>O</td><td>Outputs "L" or "H" as follows:
<table>
<tr><th colspan="2">2 BAND</th><th colspan="3">3 BAND</th><th colspan="4">4 BAND</th></tr>
<tr><th>AM</th><th>FM</th><th>LW</th><th>MW</th><th>FM</th><th>LW</th><th>SW1</th><th>SW2</th><th>FM</th></tr>
<tr><td>L</td><td>L</td><td>H</td><td>L</td><td>L</td><td>H</td><td>H</td><td>L</td><td>L</td></tr>
</table></td></tr>
<tr><td>11</td><td>$\overline{\text{IF-MUTE}}$</td><td>O</td><td>To control internal counter.</td></tr>
<tr><td>12</td><td>IFIN</td><td>I</td><td>General purpose counter input.</td></tr>
<tr><td>13</td><td>$\overline{\text{TUNE}}$</td><td>I</td><td>Receives "L" when station is tuned.</td></tr>
<tr><td>14</td><td>NC</td><td>–</td><td>Not used.</td></tr>
<tr><td>15</td><td>AM-I</td><td>I</td><td>Receives the AM local oscillator frequency signal.</td></tr>
<tr><td>16</td><td>FM-I</td><td>I</td><td>Receives the FM local oscillator frequency signal.</td></tr>
<tr><td>17</td><td>VDD</td><td>–</td><td>Supply power to IC (+5V).</td></tr>
<tr><td>18</td><td>PD</td><td>O</td><td>PLL charge pump output.</td></tr>
<tr><td>19</td><td>AIN</td><td>I</td><td rowspan="2">Nch MOS transistor for PLL active low pass filter.</td></tr>
<tr><td>20</td><td>AOUT</td><td>O</td></tr>
<tr><td>21</td><td>VSS</td><td>–</td><td>Ground.</td></tr>
</table>

IC, BA3834S

Pin No.	Pin Name	I/O	Description
1	BIASC	–	Decoupling capacitor for linear VREF connecting terminal.
2	VREFC	–	Decoupling capacitor for logic VREF connecting terminal.
3	RREF	–	Reference resistor for setting band pass filter for connecting terminal.
4, 5	NC	–	Not used.
6	DIFOUT	O	Differential amplifier output terminal.
7	CIN	I	Differential amplifier input terminal 2.
8	AIN	I	Differencial amplifier input terminal 1.
9	VCC	–	Nominally 5V.
10	A	O	Output selection control terminals (see table – 1).
11	B		
12	C		
13	SEL		
14, 15	NC	–	Not used.
16	TEST	–	Connected to ground.
17	A-OUT	O	Multiplexer output terminal.
18	GND	–	Ground.


Table – 1. Filter Select Table

SEL	A	B	C	AOUT
0	X	X	X	GND
1	0	0	0	GND
1	0	0	1	68Hz
1	0	1	0	170Hz
1	0	1	1	420Hz
1	1	0	0	1kHz
1	1	0	1	2.4kHz
1	1	1	0	5.9kHz
1	1	1	1	14.4kHz


IC, M65840FP (CX-NV51G)

Pin No.	Pin Name	I/O	Description
1	ADC	–	ADM A/D adaptive control.
2	DA1C	–	ADM D/A1 adaptive control.
3	DA2C	–	ADM D/A2 adaptive control.
4	TEST1	I	L: Normal function mode, H: test mode.
5	X-I	I	16MHz Ceramic resonator.
6	X-O	O	
7	DATA	I	Clocked serial bus data input.
8	CLK	I	Clocked serial bus clock input.
9	STB	I	Clocked serial bus strobe input.
10	TEST2	O	Test output.
11	TEST3	O	Test output.
12	REF	–	Analog 1/2Vcc, connect filter capacitor.
13	GND	–	Ground.
14	VCC	–	Nominally 5V.
15	M-O	O	Mixing key controlled low frequency signal and through outputted high frequency signal.
16	M-I	I	
17	LPF2-O	O	Forms post lowpass filter with external CR for digital key control.
18	LPF2-I	I	
19	HPF-O	O	Forms highpass filter with external CR for through outputting high frequency signal.
20	HPF-I	I	
21	LPF1-O	O	Forms pre lowpass filter with external CR for digital key control.
22	LPF1-I	I	
23	ADI-I	I	Forms integrator with external C.
24	ADI-O	O	
25	DA1I-I	I	Forms integrator with external C.
26	DA1I-O	O	
27	DA2I-I	I	Forms integrator with external C.
28	DA2I-O	O	


A MAIN C.B




J S·WAVE C.B <HE, HR, HK>



G DECK C.B



DECK-1P, DECK-2R/P/E HEAD



<TUNER SECTION>

1. Clock Frequency Adjustment
   Settings:
   - Test point: TP2 (CLK IC770 pin30)
   - Adjustment location: TC701

   Method: Set to MW 1710kHz (HE, HR, HK, LH, U, C), 1602kHz (G) and adjust TC701 so that the test point becomes 2160kHz±0.01kHz (HE, HR, HK, LH, U, C), 2052kHz±0.01 kHz (G).

2. Clock Frequency check <HD>
   Settings:
   - Test point: TP2

   Method: Set to MW 1602kHz and check that the test point is 2052kHz±0.04kHz.

3. MW VT Adjustment <HE, HR, HK>
   Settings:
   - Test point: TP1 (VT)
   - Adjustment location: L956

   Method: Set to MW 1710kHz and adjust L956 so that the test point becomes 8.5V±0.05V.
   Then set to MW 530kHz and check that the test point is more than 0.3V.

4. MW VT Check <LH, U, C, HD, G>
   Settings:
   - Test point: TP1 (VT)

   Method: Set to MW 1710kHz (LH, U, C), 1602kHz (HD, G) and check that the test point is 7.0V±1.0V (LH, U, C), 6.8V±1.0V (HD, G).

5. MW Tracking Adjustment
   <HE, HR, HK>
   Settings:
   - Test point: TP5, TP6
   - Adjustment location:
     L951 ..... 600kHz
     TC951 ..... 1400kHz

   Method: Set to TC951 to center before adjustment.
   The level at 600kHz is adjusted to MAX by L951. Then the level at 1400kHz is adjusted to MAX by TC951.

   <LH, U, C, HD, G>
   Settings:
   - Test point: TP5, TP6
   - Adjustment location: L981
     TC951 ..... 1400kHz

   Method: Set to MW 1000kHz (LH, U, C), 999kHz (HD, G) and adjust L981 so that the test point becomes maximum.

6. AM IF Adjustment
   Settings:
   - Test point: TP5, TP6
     L742 ..... 450kHz

7. SW2 VT Adjustment <HE, HR, HK>
   Settings:
   - Test point: TP1 (VT)
   - Adjustment location: L958

   Method: Set to SW2 21.85MHz and adjust L958 so that the test point becomes 8.0V±0.05V.

8. SW2 Tracking Adjustment <HE, HR, HK>
   Settings:
   - Test point: TP5, TP6
   - Adjustment location:
     L953 ..... 9.5MHz
     TC953 ..... 21.85MHz

   Method: Set up TC953 to center before adjustment.
   The level at 9.5MHz is adjusted to MAX by L953. Then the level at 21.85MHz is adjusted to MAX by TC953.

9. SW1 VT Adjustment <HE, HR, HK>
   Settings:
   - Test point: TP1 (VT)
   - Adjustment location: L957

   Method: Set to SW1 7.3MHz and adjust L957 so that the test point becomes 7.7V±0.05V.

10. SW1 Tracking Adjustment <HE, HR, HK>
    Settings:
    - Test point: TP5, TP6
    - Adjustment location:
      L952 ..... 3.2MHz
      TC952 ..... 7.3MHz

    Method: Set up TC952 to center before adjustment.
    The level at 3.2MHz is adjusted to MAX by L952. Then the level at 7.3MHz is adjusted by TC952.

11. FM VT Check
    <EXCEPT HD>
    Settings:
    - Test point: TP1 (VT)

    Method: Set to FM 87.5MHz, 108.0MHz and check that the test point is more than 1.0V (87.5MHz) and less than 8.0V (108.0MHz).

    <HD>
    Settings:
    - Test point: TP1 (VT)

    Method: Set to FM 76MHz, 108.0MHz and check that the test point is more than 0.9V (76MHz) and less than 8.7V (108.0MHz).

12. FM Tracking Check
    <EXCEPT HD>
    Settings:
    - Test point: TP5, TP6
    - Input level: 10dB

    Method: Set to FM 98.0MHz and check that the test point is 2±6dB.

    <HD>
    Settings:
    - Test point: TP5, TP6

    Method: Set to FM 83.0MHz and check that the test point is 2±6dB.

13. DC Balance/Mono Distortion Adjustment
    Settings:
    - Test point: TP3, TP4 (DC balance)
      TP5, TP6 (Distortion)
    - Adjustment location: L741
    - Input level: 54dB

    Method: Set to FM 98.0MHz and adjust L741 so that the voltage between TP3 and TP4 becomes 0V±0.04V.
    Next, check that the distortion is less than 1.3%.

14. Auto Stop Level Adjustment
    <EXCEPT HD>
    Settings:
    - Test point: TP7
    - Adjustment location: SFR722
    - Input level: 16dB

    Method: Set to FM 98.0MHz and adjust voltage low (about 0.01V) by SFR722. After that voltage high (about 7.0V) out by 2dB down.

    <HD>
    Settings:
    - Test point: TP7
    - Adjustment location: SFR722
    - Input level: 16dB

    Method: Set to FM 83.0MHz and adjust voltage low (about 0.01V) by SFR722. After that voltage high (about 7.0V) out by 2dB down.

<DECK SECTION>

15. Tape Speed Adjustment
    Settings:
    - Test tape: TTA-100 (DECK2)
    - Test point: TP8, TP9
    - Adjustment location: SFR1

    Method: Play back the test tape by DECK2 and adjust SFR1 so that the frequency counter reads 3000Hz±5Hz.

16. Azimuth Adjustment (DECK1, DECK2)
    Settings:
    - Test tape: TTA-310
    - Test point: TP8
    - Adjustment location: Head azimuth adjustment screw

    Method: Play back the 10kHz signal of the test tape and adjust screw so that the output becomes maximum. Next, perform on each FWD PLAY and REV PLAY mode.

17. PB Frequency Response Check (DECK1, DECK2)
    Settings:
    - Test tape: TTA-300
    - Test point: TP8

    Method: Play back the 315Hz and 10kHz signals of the test tape and check that the output ratio of the 10kHz signal is with respect to that of the 315Hz signal is ±2dB.

18. PB Sensitivity Adjustment
    Settings:
    - Test tape: TTA-200
    - Test point: TP8
    - Adjustment location:
      SFR301 (DECK1, Lch)
      SFR302 (DECK1, Rch)
      SFR303 (DECK2, Lch)
      SFR304 (DECK2, Rch)

    Method: Play back the test tape and adjust SFRs so that the output level of the test point becomes 300mV.

19. REC/PB Frequency Response Adjustment
    Settings:
    - Test tape: TTA-602
    - Test point: TP8
    - Input signal: 1kHz/10kHz (LINE IN)
    - Adjustment location: SFR451 (Lch)
      SFR452 (Rch)

    Method: Apply a 1kHz signal and REC mode. Then adjust OSC attenuator so that the output level at the TP8 becomes 21mV. Record and play back the 1kHz and 10kHz signals and adjust SFRs so that the output of the 10kHz signals becomes 0dB±0.5dB with respect to that of the 1kHz signal.

20. REC/PB Sensitivity Adjustment
    Settings:
    - Test tape: TTA-602
    - Test point: TP8
    - Input signal: 1kHz (LINE IN)
    - Adjustment location: SFR305 (Lch)
      SFR306 (Rch)

    Method: Apply a 1kHz signal and REC mode. Then adjust OSC attenuator so that the output level at the TP8 becomes 21mV. Record and play back the 1kHz signals and adjust SFRs so that the output is 21mV±0.5dB.

21. Bias OSC Frequency Adjustment
    Settings:
    - Test tape: TTA-601
    - Test point: TP10 (R311)
    - Adjustment location: L451

    Method: Set to the REC mode. Adjust L451 so that the frequency counter of the test point becomes minimum.

PRACTICAL SERVICE FIGURE

<TUNER SECTION>

<FM SECTION>

<EXCEPT HD>

IHF Sensitiviy:	3dB±6dB
(THD 3%)	(87.5/98.0/108.0MHz)
S/N 50dB Quieting sensitivity:	31dB±5dB
	(87.5/98.0/108.0MHz)
Signal to noise ratio:	More than 64dB
	(98.0MHz)
Distortion:	Less than 1.2% (98.0MHz)
Stereo separation:	More than 25dB (98.0MHz)
Intermediate frequency:	10.7MHz

<HD>

IHF Sensitiviy:	3dB±6dB
(THD 3%)	(76.0/83.0/90.0MHz)
S/N 50dB Quieting sensitivity:	31dB±5dB
	(76.0/83.0/90.0MHz)
Signal to noise ratio:	More than 64dB
	(83.0MHz)
Distortion:	Less than 1.2% (83.0MHz)
Stereo separation:	More than 25dB (83.0MHz)
Intermediate frequency:	10.7MHz

<AM (MW) SECTION>

Sensitivity:	48~ 62dB
(S/N 20dB)	[at 600kHz (LH, U, C)]
	[at 603kHz (HE, HR, HK, HD, G)]
	47~ 59dB
	[at 1000/1400kHz (LH, U, C)]
	[at 999/1404kHz (HE, HR, HK, HD, G)]
Distortion:	Less than 1.5%
	[at 1000kHz (LH, U, C)]
	[at 999kHz (HE, HR, HK, HD, G)]
Intermediate frequency:	450kHz

<HD>

Stereo separation:	More than 12dB
	(999kHz)

<SW1 SECTION> (HE, HR, HK)

Sensitivity:	29~ 37dB (3.2MHz)
(S/N 20dB)	26~ 34dB (5.0MHz)
	24~ 32dB (7.3MHz)
Distortion:	Less than 1.5% (5.0MHz)
Intermediate frequency:	450kHz


<SW2 SECTION> (HE, HR, HK)

Sensitivity:	45dB±5dB (9.5MHz)
(S/N 20dB)	40dB±5dB (15.0MHz)
	34dB±5dB (21.85MHz)
Distortion:	Less than 1.5% (15.0MHz)
Intermediate frequency:	450kHz

<DECK SECTION>

Tape speed:	3000Hz±45Hz
Wow & flutter:	Less than 0.4%
(W.R.M.S)	
Take-up torque:	40~ 45g-cm (FWD, REV)
F.F torque:	75~ 180g-cm
REW torque:	75~ 180g-cm
Back tension:	2~ 7.0g-cm
PB Output level:	(DECK1, 2)
	2.8V±1.5dB (SP OUT)
REC/PB Output level:	1.5±2.0dB (SP OUT)
Distortion (REC/PB):	Less than 2% (NORM, CrO_2)
Noise level (REC/PB):	Less than 8mV/15mV (DOLBY B NR ON/OFF NORM, SP OUT, Vol 2V)
	Less than 7mV/12mV (DOLBY B NR ON/OFF CrO_2, SP OUT, Vol 2V)
Crosstalk:	More than 60dB
	(1kHz, 0VU)
Erasing ratio:	More than 60dB (125Hz)
Channel separation:	More than 40dB
	(1kHz, 0VU)
REC bias frequency:	85kHz
Test tape:	NORMAL TTA-601/600
	CrO_2 TTA-610
	METAL TTA-630


A 3CD C.B


IC801
IC803
SFR1
R26
TP1 (TEO)
SFR2
TP4
39
IC1
TP2 (RF)
TP3 (VREF)
TP3 (VREF)
IC501
IC101
2
2
2
2
1
1
1


Note : Connect a probe (10 : 1) of the osilloscope to a test point.

1. Focus Bias Adjustment


Make the focus bias adjustment when replacing and repairing the optical block.



1) Connect an oscilloscope to the test points TP2 (RF) and TP3 (VREF).
2) Turn on the power switch.
3) Insert test disc TCD-782 (YEDS-18) and play back the second composition.
4) Adjust SFR2 so that RF signal of the test point TP2 (RF) is MAX and CLEARREST.




Note : The current of the laser signal can be checked with the voltages on both sides of R2 (10 Ω). The difference for the specified value shown on the lavel must be within ± 6.0mA.




$$\text{Laser current } Iop = \frac{\text{Voltage across R2}}{10\,\Omega}$$

2. TRACKING Balance Adjustment




1) Short circut between TP3 (VREF) and TP4.
2) Connect an oscilloscope to the test points TP1 (TE) and TP3 (VREF).
3) Turn on the power switch.
4) Insert test disc TCD-782 (YEDS-18) and press the PLAY button.
5) Adjust SFR1 so that the waveform on the oscilloscope is vertically symmetrical as shown in the figure below.
6) After the adjustment is completed, remove the connected lead wires from the test point TP3 (VREF) and TP4.




IC BLOCK DIAGRAM-2


IC, BA3837




IC, LA1836




IC, STK41522




IC, NJM4558M




IC, M62412P




IC, TC4094BP




IC, NJM2068M-D (T1)




IC, HA12134A




IC, DN6851




IC, BA3834S



IC, TA8124F



IC, BU4052BCP




TRUTH TABLE

CONTROL INPUTS			ON SWITCH	
INHIBIT	B	A		
L	L	L	Y0	X0
L	L	H	Y1	X1
L	H	L	Y2	X2
L	H	H	Y3	X3
H	X	X	—	—

L:LOW LEVEL
H:HIGH LEVEL
H:IRRELEVANT

MECHANICAL EXPLODED VIEW 1／1





MECHANICAL PARTS LIST 1／1

DESCRIPTIONで判断できない物は "REFERENCE NAME LIST" を参照してください。
If can't understand for Description please kindly refer to "REFERENCE NAME LIST".

REF. NO	PART NO.	カンリ NO.	DESCRIPTION
1	85-NF6-001-010		CAB,FR<50HE,50HR,50LH,50HK>
1	85-NF6-004-010		CAB,FR<50U>
1	85-NF6-065-019		CAB,FR<50G,50C>
1	85-NF6-063-019		CAB,FR<52U>
1	85-NF6-068-019		CAB,FR<54U>
1	85-NFG-001-019		CAB,FR<51GHK,51GHE,51GHD,51GHR>
1	85-NFG-004-019		CAB,FR<51GU>
2	80-VT1-202-010		FELT,12.5-15.5-2
3	85-NF5-026-010		IND,CASS
4	85-NF6-012-010		WINDOW,CASS R<EXCEPT 54U>
4	85-NF6-085-019		WINDOW,CASS R<54U>
5	85-NF6-006-010		BOX,CASS R<EXCEPT 50U,50G,52U 54U,51GU,50C>
5	85-NF6-036-010		BOX,CASS R<50U,50G,52U,51GU,50C>
5	85-NF6-072-019		BOX,CASS R<54U>
6	82-NF5-219-010		SPR-T,EJECT 2 (SIN)
7	82-NF5-218-010		SRT-T,EJECT 1 (SIN)
8	85-NF6-005-010		BOX,CASS L<EXCEPT 50U,50G,52U 54U,51GU,50C>
8	85-NF6-035-010		BOX,CASS L<50U,50G,52U,51GU,50C>
8	85-NF6-071-019		BOX,CASS L<54U>
9	85-NF6-011-010		WINDOW,CASS L<EXCEPT 54U>
9	85-NF6-084-019		WINDOW,CASS L<54U>
10	85-NF6-047-010		KEY,GEQ<EXCEPT 54U>
10	85-NF6-083-019		KEY,GEQ<54U>
11	85-NF6-007-010		PANEL,FR<EXCEPT 54U>
11	85-NF6-069-019		PANEL,FR<54U>
12	87-063-165-010		OIL-DMPR 150
13	82-NE6-067-010		BADGE AIWA 30N
14	85-NF6-017-010		KEY,PLAY<EXCEPT 54U>
14	85-NF6-080-019		KEY,PLAY<54U>
15	85-NF6-013-010		KEY,POWER<EXCEPT 54U>
15	85-NF6-079-019		KEY,POWER<54U>
16	85-NF6-009-010		WINDOW,CD
17	85-NF6-206-010		COVER,FL
18	85-NF6-014-010		KEY,OPEN<EXCEPT 54U>
18	85-NF6-073-019		KEY,OPEN<54U>
19	85-NF6-015-010		KEY,DISK<EXCEPT 54U>
19	85-NF6-074-019		KEY,DISC<54U>
20	83-NF5-020-010		KNOB,MIC<EXCEPT 54U>
20	85-NF6-078-019		KNOB,MIC<54U>
21	85-NF6-023-010		KNOB,MAIN<EXCEPT 54U>
21	85-NF6-076-019		KNOB,MAIN<54U>
22	85-NF6-024-010		IND,VOL
23	85-NF6-021-010		KEY,T-BASS<EXCEPT 54U>
23	85-NF6-082-019		KEY,T-BASS<54U>
24	85-NF6-019-010		KEY,DSP<EXCEPT 54U>
24	85-NF6-081-019		KEY,DSP<54U>
25	85-NF6-016-010		KEY,FUN ASSY
26	85-NF6-018-010		KEY,KARAOKE<50HE,50HR,50LH,50U 50HK,50G,52U,50C>
26	85-NF6-075-019		KEY,KARAOKE<54U>
27	82-NF5-212-010		GUIDE,FL
28	85-NF5-210-010		GUIDE,LED L
29	85-NF5-211-010		GUIDE,LED R
30	85-NF6-201-010		GUIDE,LED
31	85-NF6-008-010		PANEL,TRAY<50HE,50HR,50LH,50HK>
31	85-NF6-066-019		PANEL,TRAY<50U,50G,52U,50C>
31	85-NF6-077-019		PANEL,TRAY<54U>
31	85-NEG-005-019		PANEL,TRAY<51GHK,51GHE,51GHD 51GHR>
31	85-NEG-006-019		PANEL,TRAY<51GU>
32	85-NF5-007-010		CAB,STEEL<EXCEPT 54U,51GHD>
32	85-NF6-067-019		CAB,STEEL<54U>
32	85-NF5-008-010		CAB,STEEL<51GHD>
33	85-NF5-031-010		WINDOW,TOP<EXCEPT 51GU>
33	85-NFF-018-019		WINDOW,TOP<51GU>
⚠ 34	87-050-079-010		AC CORD ASSY<50HE,50HR,50LH 50HK,51GHK,51GHE,51GHR>
⚠ 34	87-050-097-010		AC CORD ASSY<51GHD>
⚠ 34	87-050-053-010		AC CORD ASSY<50U,52U,54U,51GU 50C>
⚠ 34	87-050-081-019		AC CORD ASSY<50G>
35	87-085-184-010		BUSHING,AC CORD<51GHD>
35	87-085-185-010		BUSHING,CORD<EXCEPT 50U,52U 54U,51GU,51GHD,50C>
35	87-085-189-010		BUSHING,CORD<50U,52U,54U,51GU 50C>
36	85-NF6-026-010		PANEL,REAR<50HE>
36	85-NF6-027-010		PANEL,REAR<50HR>
36	85-NF6-028-010		PANEL,REAR<50LH>
36	85-NF6-029-010		PANEL,REAR<50U>
36	85-NF6-058-019		PANEL,REAR<50HK>
36	85-NF6-062-019		PANEL,REAR<50G>
36	85-NF6-056-019		PANEL,REAR<52U>
36	85-NF6-070-019		PANEL,REAR<54U>
36	85-NFG-019-019		PANEL,REAR<51GHK>
36	85-NFG-011-019		PANEL,REAR<51GHE>
36	85-NFG-014-019		PANEL,REAR<51GU>
36	85-NFG-020-01S		PANEL,REAR<51GHD>
36	85-NFG-017-019		PANEL,REAR<51GHR>
36	85-NF6-090-019		PANEL,REAR<50C>
37	87-085-221-010		FOOT,H 13.5
38	82-NF5-227-010		HLDR,LOCK 2N
39	82-ZM3-213-010		PLATE,SHLD
40	82-NF5-229-010		PLATE,LOCK
41	82-NF5-226-010		HLDR LOCK 1N
42	82-NF5-228-010		SPR-C,LOCK
⚠ 43	87-099-811-018		PLUG,ADPTR CONV<50HK,51GHK>
A	87-067-689-010		BVTT+3-8
B	87-591-094-410		QIT + 3 - 6 GOLD
C	87-721-097-410		QT 2+3-12
D	87-067-703-010		BVT 2+3-10 W/O SLOT
E	87-067-660-010		BVT2+3-8W/O SLOT BLK
F	87-067-579-010		BVT 2+3-8 W/O SLOT
G	87-078-084-010		BVTT +3-6 W CONVEX
H	87-067-581-010		BVT2+3-15 W/O SLOT
I	87-078-019-010		S-SCREW,IT+4-6
J	87-571-092-410		VIT +3-4
K	87-067-641-010		UTT2+3-8 W/O SLOT BLK
L	87-571-032-410		VIT+2-3
M	85-NF6-205-010		PVCW,3.5-8-1.2
N	87-084-077-010		NYLON RIVET DIA 3.5-4.5

TAPE MECHANISM EXPLODED VIEW 1/1





60
57
SOL 2
DECK C.B
50
SOL 1
51
D
D
56
52
C
55
50
B
A
44
37
41
58
49
43
35
41
33
45
47
34
48
62
40
F
59
(DECK 1)
E
32
39
63
B
46
D
38
31
D
A
C
C
54
53


TAPE MECHANISM PARTS LIST 1／1

DESCRIPTIONで判断できない物は "REFERENCE NAME LIST" を参照してください。
If can't understand for Description please kindly refer to "REFERENCE NAME LIST".


REF. NO	PART NO.	ｶﾝﾘ NO.	DESCRIPTION
1	82-ZM3-214-110		CHAS ASSY,P (DECK 1)
1	82-ZM1-299-010		CHAS ASSY,R (DECK 2)
2	82-ZM1-258-010		SPR-T,PINCH L
3	82-ZM1-248-110		LVR ASSY,PINCH L
4	82-ZM1-295-210		PLATE ASSY,LINK
5	82-ZM1-266-010		LVR,DIR
6	82-ZM1-214-010		SPR-T,DIR
7	82-ZM1-206-210		CHAS,HEAD
9	82-ZM1-269-010		SPR-T,BRG
10	82-ZM1-219-010		SPR-T,LINK
11	82-ZM1-210-010		GEAR,H T
12	82-ZM1-213-010		SPR-T,HEAD
13	82-ZM1-207-010		GUIDE,TAPE
14	82-ZM1-283-210		S-SCREW,AZIMUTH
15	82-ZM1-314-110		PLATE,HEAD
16	82-ZM1-208-010		HLDR,HEAD
17	82-ZM1-218-010		SPR-E,HB
18	82-ZM1-263-110		LVR,EJECT L (DECK 1)
18	82-ZM1-264-010		LVR,EJECT R (DECK 2)
19	82-ZM1-222-010		LVR,PLAY
20	82-ZM1-217-110		REEL TABLE
21	82-ZM1-244-110		SPR-C,BT
22	82-ZM1-285-110		SPR-C,BT L
23	82-ZM1-257-010		SPR-T,CAS
24	82-ZM1-241-110		LVR,MC
25	82-ZM1-242-010		LVR,CAS
26	82-ZM1-243-010		LVR,STOP
27	82-ZM1-253-110		LVR ASSY,PINCH R
28	82-ZM1-259-010		SPR-T,PINCH R
29	82-ZM1-240-110		LVR,REC (DECK 2)
30	82-ZM1-298-010		SPR-P,EARTH
31	82-ZM1-255-110		SPR-E,LVR DIR
32	82-ZM1-221-110		GEAR,CAM
33	82-ZM1-227-110		LVR,TRIG
34	82-ZM1-224-110		LVR,FR
35	82-ZM1-265-110		SPR-E,TRIG
37	82-ZM1-223-010		GEAR,PLAY
38	82-ZM1-322-019		SPR-T,FR60
39	82-ZM1-220-210		GEAR,IDLER
40	82-ZM1-316-010		RING MAGNET 3
41	82-ZM1-216-210		GEAR,REEL
43	82-ZM1-225-010		GEAR,FR
44	82-ZM1-226-010		GEAR,REW
45	82-ZM1-228-210		SLIP DISK ASSY
46	82-ZM1-328-010		BELT FR2
47	82-ZM1-238-610		FLY-WHL ASSY,R (DECK 2)
47	82-ZM3-210-510		FLY-WHL ASSY,R2 (DECK 1)
48	82-ZM1-235-310		FLY-WHL ASSY,L (DECK 2)
48	82-ZM3-208-410		FLY-WHL ASSY,L2 (DECK 1)
49	82-ZM3-206-010		BELT,R
50	82-ZM1-245-210		HLDR,IC
51	82-ZM3-215-010		HLDR,MC
52	82-ZM3-202-010		PULLEY,MOT 2M
53	82-ZM1-288-010		SH,1.63-3.2-0.5 SLT
54	80-ZM6-243-010		SH,1.75-3.6-0.5 SLT
55	80-ZM6-230-010		SH,BELT
56	82-ZM1-308-110		CUSH-G DIA3.7-9-3.2
57	86-575-361-010		CUSH-G,6-8-0.8
58	82-ZM3-205-010		BELT,L
59	82-ZM3-204-010		PULLEY,COUPLER (DECK 1)
60	87-045-347-010		MOT,SHU2L 70(M1)
61	87-046-355-010		HEAD,PH HADKH2529B(PH)
61	87-046-356-010		HEAD,RPH HADKH5581B(RPH)
62	82-ZM1-312-010		CAPSTAN N 2.2-41.7
63	82-ZM1-313-010		CAPSTAN N 2-41.5
A	82-ZM1-315-010		S-SCREW,GVIDE TAPE
B	80-ZM6-207-010		V+1.6-7
C	82-ZM1-309-010		S-SCRW,MOTOR
D	87-067-178-010		VTT+2.6-3
E	82-ZM1-597-019		PW,2.15-6.8-0.4 SLT
F	87-067-972-010		PW,1.05-3-0.25 SLT

SPRING APPLICATION POSITION





SPEAKER EXPLODED VIEW 1／1



矢印の位置にマイナスドライバーを差し込んで、パネルをはずして、各々のスピーカー・ユニットのビスを取り、スピーカー・ユニットをはずしてください。

Insert a flat - bladed screwdriver into the position indicated by the arrows and remove the panel. Remove the screws of each speaker unit and then remove the speaker units.

SPEAKER EXPLODED VIEW 1／1 (SX-FNV50／54／50L)

DESCRIPTIONで判断できない物は "REFERENCE NAME LIST" を参照してください。
If can't understand for Description please kindly refer to "REFERENCE NAME LIST".

REF. NO	PART NO.	ｶﾝﾘ NO.	DESCRIPTION
1	85-NS6-001-019		PANEL FR<EXCEPT 54YUW>
1	85-NS6-040-019		PANEL FR<54YUW>
2	85-NS5-011-019		ADAPTOR ASSY
3	85-NS6-010-019		SPEAKER GRILL
4	85-NS6-602-019		SPEAKER WOOFER
5	83-NS8-606-019		SPEAKER MID
6	83-NS8-608-019		SPEAKER
7	85-NS6-011-019		GRILL FRAME ASSY
8	85-NS6-611-019		SPEAKER CORD Y/B<YU,Y,54YUW>
9	83-NS5-613-010		SPEAKER CORD ASSY

■ ACCESSORIES／PACKAGE LIST

DESCRIPTIONで判断できない物は “REFERENCE NAME LIST” を参照してください。
If can't understand for Description please kindly refer to “REFERENCE NAME LIST”.

NSX-V50／52／54

REF. NO	PART NO.	カンリ NO.	DESCRIPTION
1	85-NF6-901-119		IB,EAC-M<HE,HR,HK>
2	85-NF6-902-119		IB,ESF-M<LH>
3	85-NF6-903-119		IB,ESF(U)-M<UB,2UB,4UW,C>
4	85-NF6-908-019		IB,ESF(G)-M<G>
5	85-NF6-086-019		RC-T514<4UW>
6	87-006-225-019		AM LOOP ANT NC2 <EXCEPT HE,HR,HK>
7	87-006-240-019		AM LOOP ANT CON(KO) <HE,HR,HK>
8	87-043-095-019		5M(SW)WIRE-ANT(S)<HE,HR,HK>
9	87-043-115-01B		ANT,FEEDER FM
10	87-099-789-019		PLUG,ADPTR IR44 <HE,HR,HK,LH,G>

NSX-V51G

REF. NO	PART NO.	カンリ NO.	DESCRIPTION
1	85-NF6-901-110		IB,EAC-M<HE,HR,HK>
2	85-NF6-903-210		IB,ESF(U)-M<U>
3	85-NF6-909-010		IB,EAC-J<HD>
4	85-NFG-902-010		IB,EAC(HD)-J<HD>
5	85-NF5-631-010		RC-T501<EXCEPT HD>
6	85-NF6-631-010		RC-T501<HD>
7	87-006-225-010		AM LOOP ANT NC2<U,HD>
8	87-006-240-010		AM LOOP ANT CON(KO)<HE,HR,HK>
9	87-009-724-010		PLUG,ADPTR,IR39<HD>
10	87-039-929-010		CD,DGI-83299<HE,HR,HK>
11	87-043-095-010		5M(SW)WIRE-ANT(S)<HE,HR,HK>
12	87-043-115-010		ANT,FEEDER FM
13	87-050-050-010		CORD-1.5M PIN-PIN M<HD>
14	87-099-789-010		PLUG,ADPTR IR44<HE,HR>

REFERENCE NAME LIST

ELECTRICAL SECTION

DESCRIPTION	REFERENCE NAME
ANT	ANTENNAS
C-	CHIP
C-CAP	CAP, CHIP
C-CAP TN	CAP, CHIP TANTALUM
C-COIL	COIL, CHIP
C-DI	DIODE, CHIP
C-DIODE	DIODE, CHIP
C-FET	FET, CHIP
C-FOTR	FILTER, CHIP
C-JACK	JACK, CHIP
C-LED	LED, CHIP
C-RES	RES, CHIP
C-SFR	SFR, CHIP
C-SLIDE SW	SLIDE SWITCH, CHIP
C-SW	SWITCH, CHIP
C-TR	TRANSISTOR, CHIP
C-VR	VOLUME, CHIP
C-ZENER	ZENER, CHIP
CAP, CER	CAP, CERA-SOL
CAP, E	CAP, ELECT
CAP, M/F	CAP, FILM
CAP, TC	CAP, CERA-SOL
CAP, TC-U	CAP, CERA-SOL SS
CAP, TN	CAP, TANTALUM
CERA FIL	FILTER, CERAMIC
CF	FILTER, CERAMIC
DL	DELAY LINE
E/CAP	CAP, ELECT
FILT	FILTER
FLTR	FILTER
FUSE RES	RES, FUSE
MOT	MOTOR
P-DIODE	PHOTO DIODE
P-SNSR	PHOTO SENSER
P-TR	PHOTO TRANSISTOR
POLY VARI	VARIABLE CAPACITOR
PPCAP	CAP, PP
PT	POWER TRANSFORMER
PTR, RES	PTR, MELF
RC	REMOTE CONTROLLER
RES NF	RES, NON-FLAMMABLE
RESO	RESONATOR
SHLD	SHIELD
SOL	SOLENOID
SPKR	SPEAKER
SW, LVR	SWITCH, LEVER
SW, RTRY	SWITCH, ROTARY
SW, SL	SWITCH, SLIDE
TC CAP	CAP, CERA-SOL
THMS	THERMISTOR
TR	TRANSISTOR
TRIMMER	CAP, TRIMMER
TUN-CAP	VARIABLE CAPACITOR
VIB, CER	RESONATOR, CERAMIC
VIB, XTAL	RESONATOR, CRYSTAL
VR	VOLUME
ZENER	DIODE, ZENER
サージサプレッサ	SERGESUPPRESSOR
セラコン	CAP,CERA

サービス技術ニュース	
番 号	連絡内容
G－ －	
G－ －	
G－ －	

MECHANICAL SECTION

DESCRIPTION	REFERENCE NAME
ADHESHIVE	SHEET ADHESHIVE
AZ	AZIMUTH
BAR-ANT	BAR-ANTENNA
BAT	BATTERY
BATT	BATTERY
BRG	BEARING
BTN	BUTTON
CAB	CABINET
CASS	CASSETTE
CHAS	CHASSIS
CLR	COLLAR
CONT	CONTROL
CRSR	CURSOR
CU	CUSHION
CUSH	CUSHION
DIR	DIRECTION
DUBB	DUBBING
FL	FRONT LOADING
FLY-WHL	FLYWHEEL
FR	FRONT
FUN	FUNCTION
G-CU	G-CUSHION
HDL	HANDOL
HIMERON	CLOTH
HINGE, BAT	HINGE, BATTERY
HLDR	HOLDER
HT-SINK	HEAT SINK
IB	INSTRUCTION BOOKLET
IDLE	IDLER
IND, L-R	INDICATOR, L-R
KEY, CONT	KEY, CONTROL
KEY, PRGM	KEY, PROGRAM
KNOB, SL	KNOB, SLIDE
LBL	LABEL
LID, BATT	LID, BATTERY
LID, CASS	LID, CASSETTE
LVR	LEVER
P-SP	P-SPRING
PANEL, CONT	PANEL, CONTROL
PANEL, FR	PANEL, FRONT
PRGM	PROGRAM
PULLY, LOAD MO	PULLY, LOAD MOTOR
RBN	RIBBON
S-	SPECIAL
SEG	SEGMENT
SH	SHEET
SHLD-SH	SHIELD-SHEET
SL	SLIDE
SP	SPRING
SP-SCREW	SPECIAL-SCREW
SPACER, BAT	SPACER, BATTERY
SPR	SPRING
SPR-P	P-SPRING
SPR-PC-PUSH	P-SPRING, C-PUSH
T-SP	T-SPRING
TERM	TERMINAL
TRIG	TRIGGER
TUN	TUNING
VOL	VOLUME
W	WASHER
WHL	WHEEL
WORM-WHL	WORM-WHEEL
ジグアーム	ARM,SHAFT
ジグガイド	GUIDE,SHAFT
ストラップ	STRAP
トクナベ	S-SCREW
ヒンジ	HINGE
ヒンジビス	S-SCREW
ビスセレート	SCREW,SERRART

737004, 750038

アイワ株式会社
AIWA CO.,LTD.
Tokyo Japan
〒110 東京都台東区池之端１－２－11 ☎ 03 (3827) 3111 （代表）

Printed in Singapore