7. Schematic Diagram

7-1 Circuit Description

7-1-1 Overall Block Description



Part	Function
VCTi 1Chip	Treat IF+MICOM+VIDEO+MSP+Switching function.
DTV Module	Treat Channel, MPEG Decoder, AC-3 Decoder, CPU, Scaler, Video DAC, Audio function related to DTV signal.
VIDEO	Output video signal , input by Main Tuner and external equipment through VCTi Chip, as the final CRT R/G/B
SOUND	Output as Speaker through Audio Processing block and Sound AMP inside VCTi

7-1-2 Power Signal



7-1-3 Partial Block Diagram

1. Main Block Description



2. DTV MDL Block Description



MEMO

Power
Video
Audio

TP06

TP05

TP05

TP06

	Video
	Audio

TO SIDE A/V

? 7P CN702

AV1-R-IN AV1-L-IN AV1-Y-IN

SIDE A/V

M/BY

C709 47uF 16V R712 33K R711 470 Q701 KSA539-Y (TO-92)

V-MONITOR C711 100uF 16V Q702 KSC815-Y (TO-92) R710 12K R709 390 R708 390 C710 331 50V DZ705 MTZJ6.2B 6.2V R706 68

JA701 UJB-09-13P 6P

JA702 UJB-03-12A 3P

CN701 ? 6P

AV2-V-IN R713 75

M-OUT-L C704 331 50V L701 33uH (AL02)

M-OUT-R L702 33uH (AL02)

AV2-IN-L C705 331 50V

Y-IN C701 330 50V DZ702 MTZJ9.1B R703 75

AV2-IN-R

Pb-IN C702 330 50V DZ703 MTZJ9.1B R704 75

Pr-IN C703 330 50V DZ704 MTZJ9.1B R705 75

COMP-L-IN L705 33uH (AL02)

COMP-R-IN C708 331 50V L706 33uH (AL02)

C709 331 50V

SOUND AMP BLOCK

IC602 LA42032 (SIP)

RIPPLE FILTER IN1 PRE-GND IN2 STBY MUTE VCC HOUT2 -OUT2 PWR-GND -OUT1 HOUT1 N.C.

C666 10uF 50V

JA703 78716-1 4P/1C

USB-POWER USB-N USB-P

R701 27 R702 27 DZ704 MTZJ5.6B

J601 JUMPER 2001

A/3.3V R617 1K

A/14V POWER

R603 1K

R606 51K R623 10K

C620 220uF 16V Q709 KSA539-Y (TO-92) R620 4.7K

A/5V

R602 10K R609 R609

S-MUTE

C617 10uF 50V DZ605 5.6V MTZJ5.6B

C613 224 63V(P) C610 562 50V(P) R622 2K R608 10K AMP-R

C612 224 63V(P) C611 562 50V(P) R621 2K R607 10K AMP-L

CN05B 6P ?

L- L+ R- R+

? 4P CN601

Video	
Audio	

TP01



TP02



TP03



TP07



TP08



TP01

TP02

TP03

TP07

TP08

STR-W6750F CHANGE

POWER-TRANS

HOT

COLD

PHOTO-COUPLER

DEGAUSSING

VERTICAL AMP

T401 80mH/520uH HDT

FBT

Q404 FQP630TSTU (ASSY-H/S)

	Video
	Audio

CRT (MAIN SUB CRT)

V9995
PCS629-03A
8P+SEN

L502*
HF70ZBF

C508
470
3KV

R501H
1K-K
1/2W(RC)

R502H
1K-K
1/2W(RC)

CR511
1K-K
1/2W(RC)

C506
10uF
250V

R520
*
10M
1/2W

C507
10uF
250V

D504
RGP10J
600V

R519
56K
1/2W

R521*
2W(AF)
1.5(AF)

J504*
TCWA
300V

* R530
75(AF)
1/2W(AF)

C514
471
50V

C513
471
50V

C512
471
50V

Q504
KSA539-Y
(TO-92)

Q505
KSA539-Y
(TO-92)

Q506
KSA539-Y
(TO-92)

R513
12K(AF)
2W(RS)

R514
12K(AF)
2W(RS)

R515
12K(AF)
2W(RS)

R516
36K?

R517 36K ?

R518 36K ?

L503A
2.2uH

Q501
KSC2330-Y
(TO-92L)

Q502
KSC2330-Y
(TO-92L)

Q503
KSC2330-Y
(TO-92L)

R510
220
?

R511
220
?

R512
220
?

C504
821
50V

C505
821
50V

C511
821
50V

R507
47
?

R508
47
?

R509
47
?

R504
1.5K
?

R505
1.5K
?

R506
1.5K
?

R501
47
?

R502
47
?

R503
47
?

CN501
10P
?

B
G
R
GND
SE
NC
HEATER
NC

IC
G1(GND)
GK
G2(SCREEN)
RK
HEATER(-)
HEATER(+)
BK
IC

From FBT
H.V Output
F.V Output

G3(FOCUS)
G1(GND)
(FBT H.V)

RK
GK
BK
HEATER(-)
HEATER(+)
G2(SCREEN)

CRT
A51KQJ63X02(H)

GND

*GT501
1P

*GT502
1P

*GT503
1P

*GT504
1P

From FBT
S.V Output

S9501
S-23
1.5KV

S9502
S-23
1.5KV

S9503
S-23
1.5KV

S9504
S-23
1.5KV

GND_C

	Video
	Audio

JA02
JUMPER
300V


JE01
HSJ1630-010070
1P
CA05
222
16V
CA06
222
16V
RA01
100
1/2W
RA02
100
1/2W
CA03
100uF
16V
CA04
100uF
16V
CN05A
5P
?


?
7P
CN702
JA701
DPSS-9407
L704
10uH
(AL02)
L701
10uH
(AL02)
R701*
100K
C703
101
R702*
100K
C702
101
DZ703
MTZJ9.1B
9.1V
AV-R-IN
AV-L-IN
AV-Y-IN
6P
CN701